
Part Number : 733860031
Product Description : BNC Plug-to-SMA Jack, Between-Series Adapter, One Piece Per Bag, 50 Ohms
Series Number : 73386
Status : Active
Product Category : RF / Coaxial Connectors



Documents and Resources

Drawings

733860031_sd.pdf

Product Environment Compliance

Compliance

GADSL/IMDS	Not Relevant
China RoHS	per SJ/T 11365-2006
EU ELV	Not Relevant
Low-Halogen Status	Low-Halogen per IEC 61249-2-21
REACH SVHC	Contains Lead per D(2024)4144-DC (27 June 2024) SCIP:60d93d16-722f-46c6-8f7d-ecdd16606191
EU RoHS	Compliant with Exemption 6(c) per EU 2015/863

Compliance Statements

- EU RoHS
- REACH SVHC
- Low-Halogen

Industry Documents

- IPC 1752A Class C
- IPC 1752A Class D
- Molex Product Compliance Declaration
- IEC-62474
- chemSHERPA (xml)

Downloaded from Arrow.com.

Substances of Interest

- PFAS

EU RoHS Certificate of Compliance

Additional Product Compliance Information

Part Details

General

Status	Active
Category	RF / Coaxial Connectors
Series	73386
Description	BNC Plug-to-SMA Jack, Between-Series Adapter, One Piece Per Bag, 50 Ohms
Application	RF
Product Name	BNC,SMA
Style	Adapter, Between-Series Adapter
Type	Miniature
UPC	884982653429

Electrical

Frequency	4 GHz
Impedance	50Ω
Power / Voltage	VOLTAGE: 500 Vrms@Sea Level

Physical

Cable Attachment	N/A
Gender	Jack/Plug
Keying to Mating Part	N/A
Net Weight	13.241/g
Orientation	Straight
Packaging Type	Individual Bag
Panel Mount	No
Panel Mount Method	N/A
PCB Mounting	N/A
PCB Thickness - Recommended	N/A

Downloaded from Arrow.com.

Reverse Polar	No
Wire/Cable Type	N/A

Downloaded from Arrow.com.