

APC Smart-UPS RT 192V Battery Pack for Japan

SURT192XLBPJ

Overview

Lead time Usually in Stock

Main

Product or component type	Battery
Number of rack unit	3U
Number of cables	1.0
Battery type	Lead-acid battery
Provided equipment	Installation guide User manual
Range of product	Smart-UPS Battery Systems

Batteries & Runtime

Number of battery free slots	0	
Number of battery filled slots	4	
Battery voltage	192 V	
Additional information	Replace all batteries in operation together (UPS internal and external batteries) all-at- once	
Number of battery replacement quantity	2	
Replacement battery	APCRBC140J ☐	
	RBC44J-NM □	

Physical

Colour	Black
Height	13 cm
Width	43.2 cm
Depth	69.5 cm
Net weight	91 kg
Mounting mode	Rack-mounted with kit

Environmental

Ambient air temperature for operation	040 °C
Operating altitude	010000 ft
Relative humidity	095 %

Jul 4, 2025

Ambient air temperature for storage	-1545 °C
Storage altitude	015240 m
Storage Relative Humidity	0.95%

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	41.4 cm
Package 1 Width	100 cm
Package 1 Length	60 cm
Package 1 Weight	102 kg

Contractual warranty

W	arr	an	ty

2 years repair or replace, optional on-site warranties available, optional extended warranties available



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

∅ Environmental footprint

Environmental Disclosure

Product Environmental Profile

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	5ac12844-46eb-471b-94f1-318e06a714a6
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Removable battery	User replaceable
Take-back	Yes