## OPB825, OPB825A

### Obsolete (OPB825B, OPB825R)

#### Features:

- Non-contact switching
- Fast switching speed
- 0.160" (4.06 mm) wide slot
- 0.300" (7.62 mm) lead spacing





#### **Description:**

Each OPB825 and OPB825A have an infrared LED. All devices have a NPN silicon phototransistor mounted in a low-cost black plastic housing on opposite sides of a 0.160" (4.064 mm) wide slot.

OPB825 have no mounting tabs and is intended for direct insertion into PCBoards or dual-in-line sockets. OPB825A has one mounting tab on the phototransistor side.

Phototransistor switching takes place whenever an opaque object passes through the slot.

#### **Applications:**

- Non-contact interruptive object sensing
- Assembly line automation
- Machine automation
- Equipment security
- Machine safety
- Ticket Sensing

Ordering Information						
Part Number	Description					
OPB825	Slotted Switch (no tabs) IR-LED					
OPB825A	Slotted Switch (one tab) IR-LED					
OPB825B (Obsolete)	Slotted Switch (two tabs) IR-LED					
OPB825R (Obsolete)	Slotted Switch (no tabs) Red-LED					

Pin #	Description	Pin #	Description
1	Anode	3	Collector
2	Cathode	4	Emitter





General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | OPTEK Technology 2900 E. Plano Pkwy, Plano, TX 75074 | Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com

Downloaded from Arrow.com.



## **Electrical Specifications**

#### Absolute Maximum Ratings (T<sub>A</sub> = 25° C unless otherwise noted)

Storage & Operating Temperature Range	-40° C to +85° C			
Lead Soldering Temperature [1/16 inch (1.6 mm) from the case for 5 s	260° C			
nput Diode OPB8		25—A		
Forward DC Current 50 mA		A		
Peak Forward Current (1 $\mu$ s pulse width, 300 pps)	3 A	3 A		
Reverse DC Voltage	2 V			
Power Dissipation <sup>(2)</sup>	100 mW			
Output Phototransistor	OPB8	25—A		
Collector-Emitter Voltage	30 \	30 V		
Emitter-Collector Voltage	5 V	5 V		
Collector DC Current	30 m	30 mA		
Power Dissipation <sup>(2)</sup>	100 m	100 mW		



General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

© TT electronics plc

TT Electronics | OPTEK Technology 2900 E. Plano Pkwy, Plano, TX 75074 | Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com



## **Electrical Specifications**

#### OPB825, OPB825A

Electrical Characteristics (T<sub>A</sub> = 25° C unless otherwise noted)

SYMBOL	PARAMETER	MIN	ТҮР	ΜΑΧ	UNITS	TEST CONDITIONS			
Input Diode	nput Diode (See OP240 for additional information)								
V <sub>F</sub>	Forward Voltage	-	-	1.6	V	I <sub>F</sub> = 20 mA			
I <sub>R</sub>	Reverse Current		-	100	μΑ	V <sub>R</sub> = 2 V			
Output Pho	Output Phototransistor (See OP550 for additional information)								
V <sub>(BR)CEO</sub>	Collector-Emitter Breakdown Voltage	30	-	-	V	I <sub>c</sub> = 1 mA			
V <sub>(BR)ECO</sub>	Emitter-Collector Breakdown Voltage	5	-	-	V	Ι <sub>ε</sub> = 100 μΑ			
I <sub>CEO</sub>	Collector Dark Current	-	-	100	nA	$V_{CE} = 10 \text{ V}, \text{ I}_{F} = 0, \text{ E}_{E} = 0$			
Combined	Combined								
V <sub>CE(SAT)</sub>	Collector-Emitter Saturation	-	-	0.4	V	I <sub>C</sub> = 250 μA, I <sub>F</sub> = 20 mA			
I <sub>C(ON)</sub>	On-State Collector Current	1.0	-	-	mA	I <sub>F</sub> = 20 mA, V <sub>CE</sub> = 10 V			

Notes:

(1) RMA flux is recommended. Duration can be extended to 10 seconds maximum when flow soldering.

(2) Derate linearly 1.67 mW/°C above 25° C.

(3) All parameters tested using pulse techniques.

(4) Methanol or isopropanol are recommended as cleaning agents. Plastic housing is soluble in chlorinated hydrocarbons and ketones.

(5) Simulates optical path blocked with thick paper.

General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | OPTEK Technology 2900 E. Plano Pkwy, Plano, TX 75074 | Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com

## OPB825, OPB825A Obsolete (OPB825B, OPB825R)



## Performance



General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

© TT electronics plc

Rev C 04/2022 Page 4

TT Electronics | OPTEK Technology

2900 E. Plano Pkwy, Plano, TX 75074 | Ph: +1 972 323 2200

www.ttelectronics.com | sensors@ttelectronics.com

Downloaded from Arrow.com.