# EVERLIGHT ELECTRONICS CO.,LTD.

## **Technical Data Sheet**

# 0603 Package Chip LED (0.8 mm Height)

#### 19-21SYGC/S530-XX/TR8

#### **Features**

- Package in 8mm tape on 7" diameter reel.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow solder process.
- Mono-color type.
- Pb-free.
- The product itself will remain with in RoHS complaint version.

#### **Descriptions**

- The 19-21 SMD LED is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.
- Besides, lightweight makes them ideal for miniature applications. etc.

#### **Applications**

- Backlighting in dashboard and switch.
- Telecommunication: indicator and backlighting in telephone and fax.
- Flat backlight for LCD, switch and symbol.
- General use.

#### **Device Selection Guide**

D. AN.	Chip	F. 24.1 C.L.	Resin Color	
Part No.	Material	Emitted Color		
19-21SYGC/S530-XX/TR8	AlGaInP	Brilliant Yellow Green	Water Clear	



Everlight Electronics Co., Ltd.

Device No:SZDSE-191-015

http://www.everlight.com

Prepared date: 27-Oct-2007

Rev 2


Page: 1 of 9


Prepared by: Zhouhua


Downloaded from Arrow.com.




# **Package Outline Dimensions**







For reflow soldering (Propose)



**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm, Unit = mm

Everlight Electronics Co., Ltd.

Device No:SZDSE-191-015

http://www.everlight.com

Prepared date: 27-Oct-2007

Rev 2

Page: 2 of 9

Prepared by: Zhouhua



Page: 3 of 9

# **Absolute Maximum Ratings (Ta=25°C)**

Parameter	Symbol	Rating	Unit	
Reverse Voltage	$V_R$	5	V	
Forward Current	${ m I_F}$	25	mA	
Peak Forward Current (Duty 1/10 @1KHz)	$ m I_{FP}$	60	mA	
Power Dissipation	$P_d$	60	mW	
Electrostatic Discharge(HBM)	ESD	2000	V	
Operating Temperature	Topr	-40 ~ +85	$^{\circ}\!\mathbb{C}$	
Storage Temperature	Tstg	-40 ~ +90	${}^{\mathbb{C}}$	
Soldering Temperature	Tsol	Reflow Soldering: 260 °C for 10 sec.  Hand Soldering: 350 °C for 3 sec.		


# **Electro-Optical Characteristics (Ta=25°C)**

Parameter	Symbol	*Chip Rank	Min.	Тур.	Max.	Unit	Condition
Luminous Intensity		E1	11	16			
		E2	16	21			
	ntensity I <sub>v</sub>	E3	21	29		mcd	
		E4	29	34			
		E5	35	42			
Viewing Angle	$2 heta_{1/2}$			100		deg	I <sub>F</sub> =20 mA
Peak Wavelength	λp			575		nm	
Dominant Wavelength	$\lambda_d$			573		nm	
Spectrum Radiation Bandwidth	Δλ			20		nm	
Forward Voltage	$V_{\mathrm{F}}$		1.7	2.0	2.4	V	
Reverse Current	$I_R$				10	$\mu$ A	V <sub>R</sub> =5V

Everlight Electronics Co., Ltd. http://www.everlight.com Rev 2

Device No:SZDSE-191-015 Prepared date: 27-Oct-2007 Prepared by: Zhouhua

# **Typical Electro-Optical Characteristics Curves**



Everlight Electronics Co., Ltd. Device No:SZDSE-191-015

http://www.everlight.com

Rev 2 Page: 4 of 9

Prepared date: 27-Oct-2007 Prepared by: Zhouhua



## Label explanation


**CAT: Luminous Intensity Rank** 

**HUE: Dom. Wavelength Rank** 

**REF: Forward Voltage Rank** 



#### **Reel Dimensions**



**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm, Unit = mm

Everlight Electronics Co., Ltd.

Device No:SZDSE-191-015

http://www.everlight.com

Prepared date: 27-Oct-2007


Rev 2

Page: 5 of 9

Prepared by: Zhouhua




## Carrier Tape Dimensions: Loaded quantity 3000 PCS per reel



**Note:** The tolerances unless mentioned is  $\pm 0.1$ mm, Unit = mm

#### **Moisture Resistant Packaging**



Everlight Electronics Co., Ltd.

Device No:SZDSE-191-015

http://www.everlight.com

Prepared date: 27-Oct-2007

Rev 2

Page: 6 of 9

Prepared by: Zhouhua



### **Reliability Test Items And Conditions**

The reliability of products shall be satisfied with items listed below.

Confidence level: 90%

LTPD: 10%

No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260°C±5°C Min. 5sec.	6 Min.	22 PCS.	0/1
2	Temperature Cycle	$H: +100^{\circ}\mathbb{C}$ 15min $\int$ 5 min $L: -40^{\circ}\mathbb{C}$ 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	H:+100°C 5min ∫ 10 sec L:-10°C 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100°C	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40°€	1000 Hrs.	22 PCS.	0/1
6	DC Operating Life	$I_F = 20 \text{ mA}$	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85°C / 85%RH	1000 Hrs.	22 PCS.	0/1

Everlight Electronics Co., Ltd. http://www.everlight.com

Device No:SZDSE-191-015 Prepared date: 27-Oct-2007 Prepared by: Zhouhua

Rev 2

Page: 7 of 9




#### **Precautions For Use**

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big current change (Burn out will happen).

- 2. Storage
- 2.1 Do not open moisture proof bag before the products are ready to use.
- 2.2 Before opening the package: The LEDs should be kept at  $30^{\circ}$ C or less and 90%RH or less.
- 2.3 After opening the package: The LED's floor life is 1 year under 30℃ or less and 60% RH or less. If unused LEDs remain, it should be stored in moisture proof packages.
- 2.4 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.

  Baking treatment: 60±5°C for 24 hours.
- 3. Soldering Condition
- 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

Everlight Electronics Co., Ltd. http://www.everlight.com Rev 2 Page: 8 of 9

Device No:SZDSE-191-015 Prepared date: 27-Oct-2007 Prepared by: Zhouhua




#### 4. Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than  $350^{\circ}$ C for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

#### 5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



EVERLIGHT ELECTRONICS CO., LTD.

Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C Tel: 886-2-2267-2000, 2267-9936

Fax: 886-2267-6244, 2267-6189, 2267-6306

http://www.everlight.com

Everlight Electronics Co., Ltd. http://www.everlight.com Rev 2 Page: 9 of 9

Device No:SZDSE-191-015 Prepared date: 27-Oct-2007 Prepared by: Zhouhua