Please download the latest datasheet of NFE61HT332Z2A9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=NFE61HT332Z2A9%23

Note: This datasheet may be out of date.

"#" indicates a package specification code.

NFE61HT332Z2A9#









< List of part numbers with package codes >

NFE61HT332Z2A9B

NFE61HT332Z2A9K

NFE61HT332Z2A9L




Applications

| Unsuitable | Please be sure to read and comply with | |
|--------------|--|--|
| Applications | these "Precautions for use." | |
| | Automotive powertrain/safety equipment, | |
| | Automotive infotainment/comfort | |
| | equipment,Consumer equipment, | |
| | Medical [Ask Murata] | |
| | Please refer to Our Website and | |
| Specific | specifications, etc. for information about | |
| Applications | the performance, functions, quality, | |
| | management, and safety required for | |
| | the above applications, and use | |
| | Products after confirming the | |
| | performance and reliability of the actual | |
| | Product. | |



Appearance & Shape





Packaging Information

| Packaging | Specifications | Standard Packing Quantity |
|-----------|---------------------|---------------------------|
| В | Bulk(Bag) | 500 |
| K | 330mm Embossed Tape | 8000 |
| L | 180mm Embossed Tape | 2500 |



Features

The T-type chip EMI Filter NFE61HT series consists of a feedthrough capacitor and ferrite beads.

Features

- 1. Its large rated current of 2A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4. 33 to 3,300pF lineups can be used in signal lines.

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFE61HT332Z2A9#

Note: This datasheet may be out of date.

Please download the latest datasheet of NFE61HT332Z2A9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=NFE61HT332Z2A9%23

"#" indicates a package specification code.



Specifications

| Shape | SMD |
|--------------------------------|----------------|
| Size Code (in inch) | 2706 |
| Length | 6.8mm |
| Length Tolerance | +0.3/-0.5mm |
| Width | 1.6mm |
| Width Tolerance | ±0.3mm |
| Thickness | 1.6mm |
| Thickness Tolerance | ±0.3mm |
| Operating Temperature Range | -55°C to 125°C |
| Mass(typ.) | 0.062g |
| Number of Circuit | 1 |
| Rated Current | 2A |
| Rated Voltage | 100Vdc |
| Withstanding Voltage | 250Vdc |
| Insulation Resistance(min.) | 1000ΜΩ |
| Capacitance | 3300pF |
| Capacitance Tolerance | 80/-20% |
| Size Code (in mm) | 6816 |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



NFE61HT332Z2A9#


Note: This datasheet may be out of date.


Please download the latest datasheet of NFE61HT332Z2A9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-sg/products/productdetail?partno=NFE61HT332Z2A9%23

"#" indicates a package specification code.








Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.