

## Type: CLS4D14

#### **Product Description**


- 4.9 × 4.9mm Max.(L × W),1.5mm Max. Height.
- 4 Terminal pins' type gives a flexible design as inductors or transformers (SEPIC,ZETA circuit)
- · Custom design is available.




#### **Feature**

- Max. Operating frequency 1MHz, Max.
- Ideally used in portable devices such as Mobilephone, DSC/DVC, MP3, PDA, etc as DC-DC Converter inductors, specially suitable for White LED drive.
- It is possible to output high voltage and get sufficient accuracy which is hard to obtain with an ordinary inductor.
- RoHS Compliance


### **Dimensions (mm)**




### Land Pattern (mm)



## Schematics (Bottom)







For 2 in 1 Transformer



# Type: CLS4D14

## **Specification (For Inductor)**

Part Name	Stamp	Inductance ( µ H) [ Within ] 100kHz	D.C.R.(m ) Max.(Typ.) (at 20 )	Saturation Current (mA) (at 20 ) 1	Temperature rise current (mA) 2
CLS4D14-4R7N	4R7	4.7 ± 30%	110(85)	900	1000
CLS4D14-6R8N	6R8	6.8 ± 30%	130(100)	800	1000
CLS4D14-1ØØN	100	10 ± 30%	180(140)	650	850
CLS4D14-15ØN	150	15 ± 30%	270(210)	550	630
CLS4D14-22ØN	220	22 ± 30%	390(300)	450	520
CLS4D14-33ØN	330	33 ± 30%	560(430)	350	420
CLS4D14-47ØN	470	47 ± 30%	830(640)	300	330

## **Description Of Part Name**

- 1. Saturation current: The DC current at which the inductance decreases to 65% of it's nominal value.
- 2. Temperature rise current: The DC current at which the temperature rise is t = 40 .(Ta = 20).

## **Specification (For 2 in 1 Transformer)**

Sample No.	Inductance (at 100kHz)	D.C.R.(m ) Max. (at 20 )	Rated current (mA)
5362-T033	9.0 µ H ± 30%	400	410

Rated current: The DC current at which the inductance decreases to 90 % of it's initial value or when t=40, whichever is lower(Ta=20).