

Current Sense Amplifier

BD1423xFJ-EVK-001 (x: 0, 1, 2, 5, 6, 7)

BD1423xFJ-EVK-001 is an evaluation board designed for BD1423xFJ-C, ROHM's current sense amplifier.

This user's guide explains BD1423xFJ-EVK-001.

About BD1423xFJ-C (x: 0, 1, 2, 5, 6, 7)

The BD1423xFJ-C series is a current sense amplifier IC. This device operates from a single 2.7 V to 18 V power supply. It has wide common mode voltage range from -14 V to +80 V, outputs analog voltage. There are three gain types: 20 V/V, 50 V/V, and 100 V/V. By integrating matched gain resistors, gain error and offset error are minimized. In addition, the low input bias current of 1 μ A reduces offset error occurring in the connection path to the shunt resistor.

- AEC-Q100 Grade 1 qualified
- Wide Common Mode Voltage Range
- High Accuracy
- Low Offset Voltage
- Low Input Bias Current

For more detailed information about the BD1423xFJ-C, refer to the datasheet.


About BD14230FJ-EVK-001

This user's guide is an early-release version that targets the BD14230FJ-EVK-001, one of the evaluation boards in the BD1423xFJ-C series.

1. Board Information
 - Dimensions: 74 mm $\times$ 44 mm $\times$ 1.6 mm
 - Number of layers: 2
 - Material: FR-4 ($T_g \approx 125^\circ\text{C}$)
 - Copper thickness: 2 oz (70 μm)




Top side



Bottom side

Figure 1. Photograph of the BD14230FJ-EVK-001



3. Bill of Materials

Table 1. Bill of Materials of BD1423xFVJ-EVK-001

Designator	Type	Value	Package/Size	Manufacturer	Part Number
R2, R3	Resistor	100 Ω	1608 (0603)	ROHM	ESR03EZPF1000
C07	Capacitor	0.047 μ F	1608 (0603)	MURATA	GCM188R71H473KA55D
U1	Current Sense Amplifier IC	—	SOP-J8	ROHM	BD14230FJ-C
C3	Capacitor	470 pF	1608 (0603)	KYOCERA AVX	KGM15AR71H471KT
C31	Capacitor	0.1 μ F	1608 (0603)	MURATA	GCM188L81H104KA57D
R4	Resistor	1 k Ω	1608 (0603)	ROHM	ESR03EZPJ102
C2	Capacitor	0.1 μ F	1608 (0603)	MURATA	GCM188R71H104KA57D
R8, R9, R41, R73, R74, R90, R91, R92, R93, R94, R95, R96, R97	Resistor	0 Ω	1608 (0603)	ROHM	MCR03SEQPJ000
CN1	Connector	—	2 × 5 pins 2.54 mm pitch	Würth Elektronik	61301021121
CN2 *1	Connector	—	1 × 4 pins 2.54 mm pitch	Würth Elektronik	61300411121
C0, C01, C04, C05, C06, C21	Capacitor	N.M. *2	1608 (0603)	—	—
R0, R5, R6, R21, R31	Resistor	N.M.	1608 (0603)	—	—
J1, J2, J3, J4, J5, J6	Jumper	N.M.	1005 (0402)	—	—
PMR1, PMR2	Shunt Resistor (PMR series)	N.M.	6432 (2512)	ROHM	—
PSR1	Shunt Resistor (PSR series)	N.M.	6.35 × 3.05 mm	ROHM	—

*1: CN2 is not silk-screened on the PCB. It is mounted in the through-holes for GND, REF2, REF1, and VDD.

*2: N.M. = Not Mounted

4. Layout

The Top Layer Routing Diagram in Figure 4 is a reference illustration showing the design concept for signal routing and current paths during PCB design.




Figure 3. Top side PCB Image (Top View)




Figure 4. Top Layer Routing Diagram (Top View)




Figure 5. Bottom side PCB Image (Bottom View)

Notice

- 1) The information contained in this document is intended to introduce ROHM Group (hereafter referred to as ROHM) products. When using ROHM products, please verify the latest specifications or datasheets before use.
- 2) ROHM products are designed and manufactured for use in general electronic equipment and applications (such as Audio Visual equipment, Office Automation equipment, telecommunication equipment, home appliances, amusement devices, etc.) or specified in the datasheets. Therefore, please contact the ROHM sales representative before using ROHM products in equipment or devices requiring extremely high reliability and whose failure or malfunction may cause danger or injury to human life or body or other serious damage (such as medical equipment, transportation, traffic, aircraft, spacecraft, nuclear power controllers, fuel control, automotive equipment including car accessories, etc. hereafter referred to as Specific Applications). Unless otherwise agreed in writing by ROHM in advance, ROHM shall not be in any way responsible or liable for any damages, expenses, or losses incurred by you or third parties arising from the use of ROHM Products for Specific Applications.
- 3) Electronic components, including semiconductors, can fail or malfunction at a certain rate. Please be sure to implement, at your own responsibilities, adequate safety measures including but not limited to fail-safe design against physical injury, and damage to any property, which a failure or malfunction of products may cause.
- 4) The information contained in this document, including application circuit examples and their constants, is intended to explain the standard operation and usage of ROHM products, and is not intended to guarantee, either explicitly or implicitly, the operation of the product in the actual equipment it will be used. As a result, you are solely responsible for it, and you must exercise your own independent verification and judgment in the use of such information contained in this document. ROHM shall not be in any way responsible or liable for any damages, expenses, or losses incurred by you or third parties arising from the use of such information.
- 5) When exporting ROHM products or technologies described in this document to other countries, you must abide by the procedures and provisions stipulated in all applicable export laws and regulations, such as the Foreign Exchange and Foreign Trade Act and the US Export Administration Regulations, and follow the necessary procedures in accordance with these provisions.
- 6) The technical information and data described in this document, including typical application circuits, are examples only and are not intended to guarantee to be free from infringement of third parties intellectual property or other rights. ROHM does not grant any license, express or implied, to implement, use, or exploit any intellectual property or other rights owned or controlled by ROHM or any third parties with respect to the information contained herein.
- 7) No part of this document may be reprinted or reproduced in any form by any means without the prior written consent of ROHM.
- 8) All information contained in this document is current as of the date of publication and subject to change without notice. Before purchasing or using ROHM products, please confirm the latest information with the ROHM sales representative.
- 9) ROHM does not warrant that the information contained herein is error-free. ROHM shall not be in any way responsible or liable for any damages, expenses, or losses incurred by you or third parties resulting from errors contained in this document.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<https://www.rohm.com/contactus>