

MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com www.mikroe.com

Tamper 2 Click





PID: MIKROE-2552

Tamper 2 click contains a levered <u>D2HW-A221D</u> switch by <u>Omron</u>, which outputs signal in both positions - pressed and released. Omron switches, also known as microswitches, are well renowned for their reliability and endurance. The PCB of this click is designed so that the lever of the microswitch is easily accessible, making the click useful for all kinds of different applications, where precise, two position switches are required. Both the NO (Normally Open) and NC (Normally Closed) pins of the microswitch are routed to mikroBUS[™], so it can be easily connected to the microcontroller.

Switches of this kind are widely used in many different applications. The most common use of Tamper 2 click is door opening or closing detection, detecting the end of travel of a linear actuator, a Morse code input device and so on.

Tamper 2 click contains a levered <u>D2HW-A221D</u> switch by <u>Omron</u>, which outputs signal in both positions - pressed and released. Omron switches, also known as microswitches, are well renowned for their reliability and endurance. The PCB of this click is designed so that the lever of the microswitch is easily accessible, making the click useful for all kinds of different applications, where precise, two position switches are required. Both the NO (Normally Open) and NC (Normally Closed) pins of the microswitch are routed to mikroBUS[™], so it can be easily connected to the microcontroller.

Switches of this kind are widely used in many different applications. The most common use of the Tamper 2 click is door opening or closing detection, detecting the end of travel of a linear actuator, a Morse code input device and so on.

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.





ISO 27001: 2013 certification of informational security management system.
ISO 14001: 2015 certification of environmental management system.
OHSAS 18001: 2008 certification of occupational health and safety management system.





MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

www.mikroe.com

How does it work?

Tamper 2 click contains a levered D2HW-A221D microswitch by Omron, specifically positioned on the board so it is easily accessible for interacting with various objects that could press the lever, activating the microswitch that way. The microswitch is actuated by applying very little physical force, using a tipping-point mechanism which results in fast and reliable snap-in action. It also has both NC and NO contacts routed to the mikroBUS™ so both states of the switch can be detected. Both lines are equipped with the RC filters, which serve as debouncing elements for the switch and also to pull down the lines when they are left afloat. This way, the contact bouncing is reduced even further, resulting in an accurate detection of the switching event.

The switch itself is very endurable and its rated up to 42VDC / 0.5A, also can endure a very high number of switching cycles – up to 1000000.

The click board[™] also features an onboard jumper selector, which is used to select the voltage level that is connected to the microswitch input pin, making it usable for both 3V3 and 5V capable microcontoller pins.

Specifications

Туре	Pushbutton/Switches
Applications	Door opening or closing detection, detecting the end of travel of a linear actuator, a Morse code input device, etc.
On-board modules	D2HW-A221D switch by Omron
Key Features	High-quality Omron microswitch, high mechanical and electrical durability, debouncing features
Interface	GPIO
Feature	No ClickID
Compatibility	mikroBUS™
Click board size	S (28.6 x 25.4 mm)
Input Voltage	3.3V or 5V

Pinout diagram

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.





ISO 27001: 2013 certification of informational security management system.
ISO 14001: 2015 certification of environmental management system.
OHSAS 18001: 2008 certification of occupational health and safety management system.





MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 11 78 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

www.mikroe.com

This table shows how the pinout on **Tamper 2 click** corresponds to the pinout on the mikroBUS™ socket (the latter shown in the two middle columns).

Notes	Pin	mikro™ BUS				Pin	Notes
Normally closed	NCL	1	AN	PWM	16	NC	
	NC	2	RST	INT	15	NOP	Normally open
	NC	3	CS	RX	14	NC	
	NC	4	SCK	TX	13	NC	
	NC	5	MISO	SCL	12	NC	
	NC	6	MOSI	SDA	11	NC	
Power supply	3V3	7	3.3V	5V	10	5V	Power supply
Ground	GND	8	GND	GND	9	GND	Ground

Tamper 2 click electrical specifications

Description	Min	Тур	Max	Unit
Contact			100	mΩ
resistance				
Mechanical			1 milion	cycles
durability (30				
operations/min)				
Electrical			10000	cycles
durability (20				
operations/min)				

Onboard settings and indicators

Label	Name	Default	Description
JP1	VCC SEL	Left	Power supply voltage selection. Left position 3V3, right position 5V
LD1	Power LED		Power LED indicates that the click is powered on
S1	SWITCH		Onboard switch

Software support

We provide an example for the Tamper 2 click on our LibStock page, as well as a demo application (example), developed using MikroElektronika compilers. The demo can run on all the main MikroElektronika development boards.

Examples Description

The application is composed of three sections:

- System Initialization Initializes UART module used for data logging
- Application Initialization Initializes Tamper 2 click GPIO pins
- Application Task Check the state of both GPIO pins and reports current state by logging information to UART

Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.



ISO 27001: 2013 certification of informational security management system. ISO 14001: 2015 certification of environmental management system. OHSAS 18001: 2008 certification of occupational health and safety management system.





Time-saving embedded tools

MIKROELEKTRONIKA D.O.O, Batajnički drum 23, 11000 Belgrade, Serbia VAT: SR105917343 Registration No. 20490918

Phone: + 381 1178 57 600 Fax: + 381 11 63 09 644 E-mail: office@mikroe.com

```
void Tamper_2_click_Task()
{
    if (TAMPER_ON_STATE == 1)
    {
        UARTO_Write_text("Tamper 2 click is in ON statern");
    }
    if (TAMPER_OFF_STATE == 1)
    {
        UARTO_Write_text("Tamper 2 click is in OFF statern");
    }
    Delay_ms(500);
}
```

The example code for all architectures and compilers, and ready to use projects can be found on our <u>LibStock page</u>.

Other mikroE Libraries used in the example:

UART

Additional notes and information

Depending on the development board you are using, you may need <u>USB UART click</u>, <u>USB UART 2 click</u> or <u>RS232 click</u> to connect to your PC, for development systems with no UART to USB interface available on the board. The terminal available in all MikroElektronika compilers, or any other terminal application of your choice, can be used to read the message.

Resources

mikroBUS™ Standard specifications

Click board™ Catalog

Click Boards™

Downloads

D2HW-A221D datasheet

Tamper 2 click schematic

Tamper 2 click example on Libstock

Tamper 2 click 2D and 3D files



Mikroe produces entire development toolchains for all major microcontroller architectures.

Committed to excellency, we are dedicated to helping engineers bring the project development up to speed and achieve outstanding results.



