Data Sheet | Item Number: 285-135 2-conductor through terminal block; 35 mm²; lateral marker slots; only for DIN 35 x 15 rail; POWER CAGE CLAMP; 35,00 mm²; gray https://www.wago.com/285-135





Color: 🔳 gray

Through terminal block, 285 Series, power cage clamp

Quick and easy connections are guaranteed with this through terminal block (item number 285-135). Strip lengths must be 25 mm when connecting conductors to this through terminal block. This product features conductor terminals and utilizes POWER CAGE CLAMP. The POWER CAGE CLAMP is perfect for connecting large conductor cross-sections. This universal connector is both reliable and maintenance-free. What's more, you can use it to connect all types of conductors and the clamping point can be locked open, making it easier to use. You do not need to use a torque wrench or prepare the conductor. For example, crimping ferrules is not necessary. Depending on the type of conductor, this through terminal block is designed for conductor cross sections ranging from 6 mm² to 35 mm². It features one level and two clamping points for connecting a single potential. The gray housing is made of polyamide (PA66) for insulation. These high-current terminal blocks are mounted using DIN-rails 35 x 15..

FI	ect	ric	alo	dat:

Ratings per	IEC/	IEC/EN 60947-7-1		Approvals per		UL 1059	
Overvoltage category	III	III	Ш	Use group	В	С	D
Pollution degree	3	2	2	Rated voltage	600 V	600 V	-
Nominal voltage	1000 V	-	-	Rated current	115 A	115 A	-
Rated surge voltage	8 kV	-	-				
Rated current	125 A	-	-				

Approvals per	CSA 22.2 No 158		
Use group	В	С	D
Rated voltage	600 V	600 V	-
Rated current	115 A	-	-

Power Loss	
Power loss, per pole (potential)	4.0625 W
Rated current ${\rm I}_{\rm N}$ for specified power loss	125 A
Resistance value for specified, current- dependent power loss	0.00026 Ω

Connection data

Clamping units	2	
Total number of potentials	1	
Number of levels	1	
Number of jumper slots	2	

Connection 1	
Connection technology	POWER CAGE CLAMP
Actuation type	Operating tool
Connectable conductor materials	Copper
Nominal cross-section	35 mm²
Solid conductor	6 35 mm² / 8 2 AWG
Stranded conductor	6 35 mm² / 8 2 AWG
Fine-stranded conductor	6 35 mm² / 8 2 AWG
Fine-stranded conductor; with insulated ferrule	6 35 mm² / 8 2 AWG

Data Sheet | Item Number: 285-135 https://www.wago.com/285-135

N/AI	5
------	---

Connection 1	
Fine-stranded conductor; with uninsula- ted ferrule	6 35 mm² / 8 2 AWG
Strip length	25 mm / 0.98 inches
Wiring direction	Side-entry wiring

Physical data	
Width	16 mm / 0.63 inches
Height	86 mm / 3.386 inches
Depth from upper-edge of DIN-rail	63 mm / 2.48 inches

Mechanical data	
Mounting type	DIN-rail 35 x 15
Mounting (note)	only suitable for DIN 35 x 15 rail
Marking level	Side marking

Material data	
Note (material data)	Information on material analitications can be found have
	Information on material specifications can be found here
Color	gray
Material group	I
Insulation material (main housing)	Polyamide (PA66)
Flammability class per UL94	VO
Fire load	1.257 MJ
Weight	79.3 g

Environmental requirements			
Processing temperature	-35 +85 °C	Environmental Testing (Environme	ntal Conditions)
Continuous operating temperature -	-60 +105 ℃	Test specification Railway applications – Rolling stock – Electronic equipment	DIN EN 50155 (VDE 0115-200):2022-06
		Test procedure Railway applications – Rolling stock equipment – Shock and vibration tests	DIN EN 61373 (VDE 0115-0106):2011-04
		Spectrum/Installation location	Service life test, Category 1, Class A/B
		Function test with noise-like vibration	Test passed according to Section 8 of the standard
		Frequency	$f_1 = 5 Hz \text{ to } f_2 = 150 Hz$ $f_1 = 5 Hz \text{ to } f_2 = 150 Hz$
		Acceleration	0.101g (highest test level used for all axes) 0.572g (highest test level used for all axes) 5g (highest test level used for all axes)
		Test duration per axis	10 min. 5 h
		Test directions	X, Y and Z axes X, Y and Z axes X, Y and Z axes
		Monitoring for contact faults/interruptions	Passed
		Voltage drop measurement before and after each axis	Passed
		Simulated service life test through incre- ased levels of noise-like vibration	Test passed according to Section 9 of the standard
		Extended test scope: Monitoring for con- tact faults/interruptions	Passed Passed
Page 2/9	Version 0	06.05.2025	Continued on next page

Data Sheet | Item Number: 285-135 https://www.wago.com/285-135



Environmental Testing (Environmental Conditions)	
--	--

Extended test scope: Voltage drop mea- surement before and after each axis	Passed Passed
Shock test	Test passed according to Section 10 of the standard
Shock form	Half sine
Shock duration	30 ms
Number of shocks per axis	3 pos. und 3 neg.
Vibration and shock stress for rolling stock equipment	Passed

Commercial data	
Product Group	1 (Rail Mounted Terminal Blocks)
PU (SPU)	15 pcs
Packaging type	Box
Country of origin	PL
GTIN	4045454507381
Customs tariff number	85369010000

Product classification	
UNSPSC	39121410
eCl@ss 10.0	27-14-11-20
eCl@ss 9.0	27-14-11-20
ETIM 9.0	EC000897
ETIM 8.0	EC000897
ECCN	NO US CLASSIFICATION

Environmental Product Compliance

RoHS Compliance Status

Compliant,No Exemption

Approvals / Certificates

General approvals



Approval	Standard	Certificate Name
CCA DEKRA Certification B.V.	EN 60947	NTR NL-7707
CSA DEKRA Certification B.V.	C22.2 No. 158	154112
KEMA/KEUR DEKRA Certification B.V.	EN 60947	71-105562
UL Underwriters Laboratories Inc.	UL 1059	E45172

Declarations of conformity and manufacturer's declarations



Approval	Standard	Certificate Name
EU-Declaration of Confor- mity WAGO GmbH & Co. KG	-	-
Railway WAGO GmbH & Co. KG	-	Z00004420.000
UK-Declaration of Confor- mity WAGO GmbH & Co. KG	-	-

https://www.wago.com/285-135

Approvals for marine applications





Approval	Standard	Certificate Name
ABS American Bureau of Ship- ping	EN 60947	20-HG1941090-PDA
DNV GL Det Norske Veritas, Ger- manischer Lloyd	-	TAE00001V2

Downloads

Environmental Product Compliance

Compliance Search	
Environmental Product Compliance 285-135	$\underline{\checkmark}$

Documentation

Bid Text			
285-135	19.02.2019	xml 3.23 KB	$\underline{\downarrow}$
285-135	04.01.2018	doc 23.50 KB	\downarrow

CAD/CAE-Data

CAD data	CAE data
2D/3D Models 285-135	EPLAN Data Portal 285-135
	WSCAD Universe 285-135
	ZUKEN Portal 285-135

1 Compatible Products		
1.1 Optional Accessories		
1.1.1 Cover		
1.1.1.1 Cover		
1		
Item No.: 285-421 Finger guard; touchproof cover protects unused conductor entries; for 35 mm ² high-current tbs; yellow		

https://www.wago.com/285-135

1.1.2 DIN-rail

1.1.2.1 Mounting accessories



Copper carrier rail; 35 x 15 mm; 2.3 mm thick; 2 m long; unslotted; according to EN 60715; copper-colored



Item No.: 210-114

Steel carrier rail; 35 x 15 mm; 1.5 mm thick; 2 m long; unslotted; similar to EN 60715; silver-colored



Steel carrier rail; 35 x 15 mm; 1.5 mm thick; 2 m long; slotted; galvanized; similar to EN 60715; silver-colored



Item No.: 210-118 Steel carrier rail; 35 x 15 mm; 2.3 mm thick; 2 m long; unslotted; according to EN 60715; silver-colored Item No.: 210-197 Steel carrier rail; 35 x 15 mm; 1.5 mm thick; 2 m long; slotted; similar to EN 60715; silver-colored



Item No.: 210-506 Steel carrier rail; 35 x 15 mm; 1.5 mm thick; 2 m long; unslotted; galvanized; similar to EN 60715; silver-colored

1.1.3 Ferrule

1.1.3.1 Ferrule

Item No.: 216-413 Ferrule; Sleeve for 25 mm² / AWG 4; uninsulated; electro-tin plated; electrolytic copper; gastight crimped; acc. to DIN

46228, Part 1/08.92; silver-colored

Item No.: 216-414

Ferrule; Sleeve for 35 mm² / AWG 2; uninsulated; electro-tin plated; electrolytic copper; gastight crimped; acc. to DIN 46228, Part 1/08.92; silver-colored

1.1.4 Installation

1.1.4.1 Mounting accessories

Item No.: 249-117 Screwless end stop; 10 mm wide; for DINrail 35 x 15 and 35 x 7.5; gray







https://www.wago.com/285-135

1.1.6 Marking

1.1.6.1 Group marker carrier



<u>Item No.: 249-105</u> Group marker carrier; gray





https://www.wago.com/285-135

1.1.6.4 Marking strip

0

Item No.: 2009-110

Marking strips; for Smart Printer; on reel; not stretchable; plain; snap-on type; white





Data Sheet | Item Number: 285-135 https://www.wago.com/285-135



Installation Notes

Installation



Snapping a terminal block onto DIN-rail (to the left or to the right).



Removing a terminal block from the assembly (to the left or to the right).

Conductor termination



Conductor termination - step 1: Rotate the operating tool (5.5 mm blade width) counter-clockwise. Next, push in the orange locking tab. The clamp is locked open for hands-free wiring.



Conductor termination – step 2: Insert a stripped conductor into the clamping unit until it hits the backstop. Hold in this position.



Conductor termination - step 3: A short counter-clockwise rotation closes the clamp, securing the conductor . When unlocked, allow the operating tool to rotate clockwise to securely terminate the conductor.



Side-entry wiring means that even larger conductors, which have limited flexibility, can be easily connected.

Commoning



Commoning adjacent terminal blocks using a centrally positioned push-in jumper.



Slide the marking strip laterally to remove the jumper.

Commoning



Commoning 35 mm² (2 AWG) POWER CA-GE CLAMP Terminal Blocks with 10/16 mm² (8/6 AWG) 2010 and 2016 Series TOPJOP® S Terminal Blocks using stepdown jumpers (not valid for Item No. 2016-76xx and Item No. 2016-77xx).



Step-down jumpers common terminal blocks of different sizes, without losing a conductor clamping point. This can be beneficial on long conductor runs where voltage drop can be a problem. A large conductor can be easily connected to smaller conductors at the distribution point.

Step-down jumpers are simply pushed down for full insertion, similar to adjacent jumpers. Commoning may be made in either direction using the special thin end plate to cover the open side. Additional through terminal blocks having a smaller cross-section may be commoned using adjacent jumpers.

The following should be noted: The total current of the outgoing circuits does not exceed the nominal current of the step-down jumper.

https://www.wago.com/285-135

Power tap





The power tap is inserted into the jumper contact slot. It can be fitted with a strain relief plate.



Power tap inserted in a jumper contact slot



Always push voltage tap (Item No. 283-407) down into the terminal block until fully inserted!

Testing



Testing Voltage measurements can be performed, e.g., using a 2-pole voltage tester (Item No. 206-707).



Testing with test plug adapter (Item No. 283-404).

Marking



WMB markers or self-adhesive, printable marking strips can be accommodated on 35, 50 and 95 mm² high-current terminal blocks.



Marker carrier (Item No. 285-442) for marking strips (Item No. 2009-110) or 2 WMB markers for 285-13x, 285-15x and 285-19x Terminal Blocks

Subject to changes. Please also observe the further product documentation!