



Product Status: **Not Recommended for new design-ins**

CONTACT US

DC-DC APPLICATION NOTES

Technical Information

Input Voltage Range (V)	18 to 36
Design Origin	Murata Power Solutions
Dimensions (inch)	1 x 1 x 0.45
Efficiency (%)	79
Form Factor	1 x 1
Mounting Type	Surface Mount
Output Current (A)	1
Isolation (Vdc)	1500
Operating Temp. Range (C)	-40 to 65
Ripple Noise (mV pk-pk)	120
Total Output Power (W)	5
Output Voltage 1 (V)	5
Input Voltage Nominal (V)	24