

# POWR-GARD® Blocks & Holders

## LPHV POWR-SAFE FUSE HOLDERS

1000 V dc



### Description

The Littelfuse LPHV fuse holder is designed to house 1000 V fuses. It is not designed for load break but is ideal for isolating photovoltaic module strings for maintenance and meets UL requirements for 1000 V solar fuse protection

### Features/Benefits

- Touch-safe design offers protection when replacing fuses
- Compact design
- 35 mm DIN Rail Mountable
- Available in 1-, 2-, 3- and 4-pole configurations
- No fuse pullers or tools required for fuse removal
- Meets IEC 60269-2, -4, -6 performance requirements

### Multi-Pole Assembly Kit


Kits are used to create multi-pole holders from 1-pole LPHV fuse holders.

**Multi Pole Assembly Kit Ordering No. CYHP0001Z-KIT**  
(Kit contains 20 connector pincers & 10 handle pins).

### Ordering Information

SERIES	POLES	CATALOG NUMBER	ORDERING NUMBER	TERMINAL TYPE	WIRE TYPE	WIRE RANGE	TERMINAL TORQUE	ROHS
LPHV	1	LPHV001	LPHV0001Z	Pressure Plate	75° C or 90° C CU Only	Stranded / [Solid]	#8-14 AWG (2-10 mm²) / [#10-14 AWG (2-6 mm²)]	17.7 in-lbs (2 N-m)
LPHV	2	LPHV002	LPHV0002Z					
LPHV	3	LPHV003	LPHV0003Z					
LPHV	4	LPHV004	LPHV0004Z					

### Dimensions Inches (mm)



Look for this logo to indicate products that are used in solar applications. Visit our website [Littelfuse.com/solar](http://Littelfuse.com/solar) for the latest updates on approvals, certifications, and new products.

**Disclaimer Notice** – Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at [www.littelfuse.com/product-disclaimer](http://www.littelfuse.com/product-disclaimer).



Expertise Applied | Answers Delivered