

#### BeStar Technologies Inc.

Address: 761 N. 17th Street Unit 4, St. Charles, IL 60174
Tel: 847-261-2850 E-mail: sales@bestartech.com Web: www.bestartech.com

Document Number: 0005-20 Revision : A6 **Total Pages** : 5

Prepare by : Loki, Lo

Date : 24 September, 2018

# **SoniCrest** Brand Acoustic Components

www.jlsonicrest.com

Document Type : Specification

Product Type : Electro-magnetic Sound Generator Component

Part Number : HCM2606BX

A2 - Updated format and layout by Leo Sin on 20 Feb., 2006	A6 - Updated section 4 - 6 by Loki, Lo on 24 Sept., 2018	
A3 - Updated marking by Leo Sin on 22 Feb., 2006		
A4 - Updated RoHS version by Leo Sin on 10 May, 2006		
A5 - Updated section 4 by Leo Sin on 22 Aug., 2006		

This material is the property of BeStar Technologies Inc. Unauthorized copying or use of this material is prohibited. **HCM2606BX** Page 2 of 5

### 1. Purpose and Scope

This document contains both general requirements, qualification requirements, and those specific electrical, mechanical requirements for this part.

### 2. Description

26 x 26 mm electro-magnetic sound generator with built-in oscillation circuit, RoHS compliant.

### 3. Application

Computers and Peripherals, Portable Equipment, Automobile Electronics, POS System, Household Appilances, etc.

#### 4. Component Requirement

# 4.1. General Requirement

**4.1.1.** Operating Temperature Range : -20°C to +60°C

**4.1.2.** Storage Temperature Range : -30°C to +70°C

**4.1.3.** Weight : Approx. 17g

**4.1.4.** Housing Material : ABS

### 4.2. Electrical Requirement

**4.2.1.** Rated Voltage : 6V

**4.2.2.** Operating Voltage : 4 ~ 8 V

**4.2.3.** Rated Current : <=65mA

**4.2.4.** Generated Frequency :  $400 \pm 100 \text{ Hz}$ 

**4.2.5.** Sound Pressure Level at 10cm : >=95dB

(Applying rated voltage)

#### 4.3. Mechanical Requirement

**4.3.1.** Layout and Dimension : See Section 6, Figure 3

HCM2606BX Page 3 of 5

### 4.4. Test Setup of SPL and Frequency Measurement




Figure 1. Frequency Testing Circuit




Figure 2. SPL Inspection Test Setup

**Notes**: Input 6V DC into samples. Measure SPL using a calibrated SPL meter 10cm from the alert port. Sound level meter to be in accordance with IEC651 (1979) Type 1 and/or ANSI S1.4-1983. The meter must be checked on a daily basis using a calibrated acoustic calibrator recommended by the manufacturer. Measurement should be carried out in a free field environment or at least 40cm from any surface.

HCM2606BX Page 4 of 5

#### 5. Reliability Test

**5.1. Operating Life**: Subject samples to room condition for 96 hours with rated voltage. Components must be fully stabilized before data is taken, which may require up to a 2 hours soak.

- **5.2. High Temperature**: Subject samples to +70°C for 72 hours with rated voltage. Components must be fully stabilized at temperature extrems before data is taken, which may require up to a 2 hours soak.
- **5.3. Low Temperature**: Subject samples to -30°C for 72 hours with rated voltage. Components must be fully stabilized at temperature extrems before data is taken, which may require up to a 2 hours soak.
- **5.4. Temperature Shock**: Each temperature cycle shall consist of 30 minutes at -30°C, 15 minutes at +20°C, 30 minutes at +70°C and 15 minutes at +20°C. Test duration is for 10 cycles.
- **5.5. Static Humidity**: Precondition at room temperature for 1 hour. Then expose to +40°C with 90 to 95% relative humidity for 96 hours. Finally dry at room ambient for 2 hours before taking final measurement.
- **5.6. Random Vibration**: Secure samples. Vibrated randomly  $10Hz \sim 50Hz$  with 1.5mm peak amplitude and 1 minutes sweep duration. The test duration is 30 minutes per plane (x, y, z).
- **5.7. Drop Test**: Drop samples naturally from the height of 0.8m onto a wooden board six times.
- **5.8. Solderability**: 235°C±5°C for 2±0.5 seconds.

HCM2606BX Page 5 of 5

# 6. Mechanical Layout

Unit: mm

Tolerance : Linear  $XX.X = \pm 0.5$ 

 $XX.XX = \pm 0.05$ 

Angular =  $\pm 0.25^{\circ}$ 

(unless otherwise specified)




Figure 3. HCM2606BX Mechanical Layout