

DLW21SH121HQ2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW21SH121HQ2# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=DLW21SH121HQ2%23

"#"at the end indicates the package specification code.









< List of part numbers with package codes > DLW21SH121HQ2B DLW21SH121HQ2L



Applications

| Unsuitable | Please be sure to read and comply with |
|-----------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Applications | these "Precautions for use." |
| Specific Applications | Automotive powertrain/safety equipment, Automotive infotainment/comfort equipment,Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual |
| | Product. |
| Recommended | Automotive powertrain/safety equipment, |
| Applications | LVDS |



Packaging Information

| | | Standard |
|-----------|---------------------|----------|
| Packaging | Specifications | Packing |
| | | Quantity |
| В | Bulk(Bag) | 500 |
| L | 180mm Embossed Tape | 2000 |



Features


- 1. Small size: 2.0x1.2x1.2mm
- 2. Available for high density mounting (Narrow pitch)
- ■Application

Common mode noise suppression for automotive interfaces such as USB,LVDS,PCIe



Appearance & Shape





1 of 3

Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- $2. This \ data{sheet has only typical specifications because there is no \ space for \ detailed \ specifications.}$

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





DLW21SH121HQ2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW21SH121HQ2# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=DLW21SH121HQ2%23

"#"at the end indicates the package specification code.



Specifications

| Shape | SMD |
|---------------------------------------------------|-------------------------------------------------------------------|
| Size Code (in mm) | 2012 |
| Size Code (in inch) | 0805 |
| Length | 2.0mm |
| Length Tolerance | ±0.2mm |
| Width | 1.2mm |
| Width Tolerance | ±0.2mm |
| Thickness | 1.2mm |
| Thickness Tolerance | ±0.2mm |
| Common Mode Impedance (at 100MHz) | 120Ω |
| Common Mode Impedance (at 100MHz) Tolerance | ±25% |
| Rated Current | 280mA |
| Derating of Rated Current | Yes (Over 105°C) *For details, please check the derating diagram. |
| Rated Voltage | 20Vdc |
| Withstanding Voltage | 50Vdc |
| DC Resistance(max.) | 0.416Ω |
| DC Resistance | 0.32Ω±30% |
| Insulation Resistance(min.) | 10ΜΩ |
| Operating Temperature Range | -40°C to 125°C |
| Mass(typ.) | 0.011g |
| Number of Circuit | 1 |
| Operating Temperature Range(Self-temperature rise | No |

| 1 | | |
|---|-------|--------|
| | Brand | Murata |
| | | |

2 of 3

Attention

is included)

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



DLW21SH121HQ2#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.


Please download the latest datasheet of DLW21SH121HQ2# from the official website of Murata

http://www.murata.com/en/products/productdetail?partno=DLW21SH121HQ2%2

"#"at the end indicates the package specification code.

Product Data






Impedance-Frequency Characteristics

In operating temperature exceeding +105°C, derating of current is necessary for this series.


Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current




Impedance-Frequency Characteristics (Main Items)

■ Equivalent Circuit (Note 1)



Note1: The Port/Pin No. of the Simulation Model provided by our company is



E : 1 (0:

Equivalent Circuit

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

Derating of Rated Current

3 of 3