Fusion PCB/PCBA

() seeed

Q Sign in



Description Documents Reviews FAQS The Loco Positioning Node is a versatile positioning device that can run either as an Anchor or Tag in a Loco Positioning system. The system measures the distance between Nodes and Tags, and from those distances, the absolute position of objects carrying Tags can be calculated. For more information on the Loco Positioning System please see this <u>Loco Positioning System page</u> Specifications are based on the standard 2-way ranging mode. · Supports Anchor, Tag or Sniffer mode Can be used as a standalone system with some Nodes acting as Anchors and one or more nodes acting as Tags Multiple powering options · Onboard MCU Electrical specification Based on the Decawave DWM1000 module Implements IEEE 802.15.4 UWB STM32F072 MCU (Cortex-M0, 48MHz, 16kb SRAM, 128kb flash) • High precision pressure sensor (LPS25H) uUSB connector Full speed USB device interface • Powered by USB, 6 mm barrel jack (5 - 12V) or screw terminal (5 - 12V) FTDI debug port (not populated)

Serial connector compatible with ESP8266 module (not populated) Power consumption 180 mA max Ranging specification  $\bullet \ \ \text{Ranging accuracy} \pm 10 \ \text{cm} \ \text{according to} \ DWM1000 \ \text{spec}. \ \text{See} \ \underline{\text{the wiki}} \ \text{for measurements}.$ · Maximum tested range 10 m • Nr of anchors required: theoretical minimum of 4 for 3D positioning. More anchors add redundancy and accuracy, up to 8 Radio specification • Operates at 3.2 - 7 GHz Channel bandwidth 500 MHz Mechanical specification • Weight: 13.3 g • Size (WxHxD): 65x40x13 mm • 4 mounting holes for M3 screws Compatibility Works with the Loco Positioning Deck Part List 1 x Loco Positioning Node ECCN/HTS ECCN EAR99 HSCODE 8543709990 8526910020

Bundle Sales

+ 

This item: DWM1000 Node

□ Crazyflie 2.0 DWM1000 Deck

 Company
 Help Center
 Community

 About Seed
 How to Get Help
 Project Hub

 Distributors
 FAQ
 Forum

 Careers
 Technical Support
 Blog

 Shipping & Order
 Wiki



Warranty & Returns
Payment Information

© 2008-2019 Seeed Technology Co.,Ltd. All rights reserved. Site Map Privacy Policy PayPal VISA 🖭 👽 Market





