

# APC Smart-UPS RT 15kVA, 208V, LCD, rackmount, 12U, 4x NEMA L6-20R & 2x NEMA L6-30R outlets

SURT15KRMXLT

#### Overview

Lead time Usually Ships within 2 Weeks

#### Main

IVIAIII		
Main Input Voltage	208 V	
Product or component type	Uninterruptible power supply (UPS)	
Other Input Voltage	240 V	
Main Output Voltage	208 V	
Other Output Voltage	240 V	
Rated power in W	12000 W	
Rated power in VA	15000 VA	
output connection type	4 NEMA L6-20R 2 NEMA L6-30R	
Output connector type	Hard wire 3-wire (2P + E) 1	
Number of rack unit	12U	
Provided equipment	CD with software Rack mounting support rails Smart UPS signalling RS-232 cable User manual Web/SNMP management card	
Range of product	Smart-UPS On-Line	

#### **Batteries & Runtime**

Run Time	View Runtime Graph ☐	
Efficiency	View Efficiency Graph ☐	
Battery type	Lead-acid battery	
Battery voltage	+/- 192 V (split battery referenced to neutral)	
Extended runtime	1	
Number of battery filled slots	4	
Number of battery free slots	0	
Battery recharge time	2 h	
Number of battery replacement quantity	4	
Battery life	35 year(s)	
Replacement battery	APCRBC140 ☐	

Discharge battery voltage	+/- 154 V
Battery charger power	1910 W rated

## General

Number of power module filled slots	0
Number of power module free slots	0
Redundant	No
UPS type	Double conversion online

# **Physical**

•	
Colour	Black
Height	53.3 cm
Width	43.2 cm
Depth	77.3 cm
Net weight	247.73 kg
Mounting location	Front
Mounting preference	Lower
Mounting mode	Rack-mounted
Two post mountable	0
USB compatible	No

# Input

Maximum input current	85 A	
Input harmonic distortion	Less than 5 % for full load	
Input Power Factor at Full Load	0.99	
Switching current capacity	100 A	
Input voltage limits	160280 V	
Number of input connectors	1 hard wire 3-wire (2P + E)	
Network frequency	4070 Hz auto-sensing	

# Output

Bypass type	Built-in static bypass Internal bypass (automatic and manual) Optional external bypass	
Crest factor	3:1	
Harmonic distortion	Less than 5 %	
Maximum configurable power in VA	15000 VA	
Maximum configurable power in W	12000 W	
Output overload operation	60 seconds at 125% and 30 seconds at 150%	
Wave type	Sine wave	
Efficiency	93 % (in battery operation)	
Output frequency	50/60 Hz +/- 3 Hz user adjustable +/- 0.1 Hz sync to mains	

Additional information Configurable for 208 or 240 nominal output voltage

#### **Conformance**

Product certifications UL 1778

#### **Environmental**

Acoustic level	50 dBA	
Heat dissipation	2610 Btu/h	
Operating altitude	010000 ft	
Ambient air temperature for operation	040 °C	
Ambient air temperature for storage	-1545 °C	
Storage altitude	015240 m	
IP degree of protection	IP20	
Relative humidity	095 % non-condensing	
Storage Relative Humidity	095 % non-condensing	

### **Communications & Management**

Emergency power off	Yes 0	
Free slots		
Preinstalled device	Network management card 2 with environmental monitoring	

## **Surge Protection and Filtering**

Noise suppression Full time multi-pole noise filtering : 0.3% IEEE surge let-through : zero clamping

response time : meets UL 1449

## **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	99 cm
Package 1 Width	100.3 cm
Package 1 Length	61 cm
Package 1 Weight	314.09 kg

## **Contractual warranty**

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

#### Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Total lifecycle Carbon footprint	29265
Environmental Disclosure	Product Environmental Profile

#### **Use Better**

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
Energy Efficiency Optimized	Energy efficient product

#### **Use Again**

○ Repack and remanufacture	
End of life manual availability	End of Life Information
Removable battery	User replaceable
Take-back	Yes
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins