# RF / Audio Generators





# Model 2005B

### 150 MHz RF Signal Generator

- 100 kHz to 150 MHz on six bands
- Output to 450 MHz on harmonics
- AM modulation, internal or external ■ Frequency monitor output for external
- Frequency monitor output for external frequency counter
- Step and variable attenuation

Specifications model		
	2005B	
MAIN OUTPUT		
Frequency Range	100 kHz to 150 MHz (up to 450 MHz on third harmonics)	
rrequency runge	A) 100 kHz-300 kHz	
	B) 300 kHz-1 MHz	
	C) 1 MHz-3.2 MHz	
	D) 3 MHz-10 MHz	
	E) 10 MHz-35 MHz	
	F) 32 MHz-150MHz	
	(96-450 MHz on harmonics)	
Dial Accuracy	±3%	
RF Output Level	Continuously variable. Step attenuator provides approximately	
la Gatpat Eever	20 dB of attenuation	
Maximum Output	Approximately 100 mV rms to 35 MHz. Continuously variable	
	in hi or lo step, at least 20 dB range of adjustment	
	<u> </u>	
FREQUENCY MONITOR OUTPUT		
Frequency	100 kHz to 150 MHz	
Level	50 mV rms min. fixed, unmodulated signal	
AMPLITUDE MODULATION		
Internal	Frequency 1 kHz; level continuously variable. Modulation signal	
	available at front panel jack; fixed 1 V rms (min) into approx. 10 $k\Omega$	
External	Frequency 50 Hz to 20 kHz	
Sensitivity	Approximately 100 mV rms	
POWER SOURCE	120/220/240V ±10%, 50/60 Hz	
GENERAL		
Dimensions (HxWxD)	5.91 x 9.84 x 5.12" (150 x 250 x 130 mm)	

## **Accessories**

5.5 lbs. (2.5 kg)

One Year Warranty

SUPPLIED: BNC to Insulated Clip Output Cable, Detachable Power Cord, Instruction Manual



3001

# Model 3001

# 20 Hz-I 50 kHz Sine/Square Wave Audio Generator

- Sine and square wave generator
- 20 Hz to 150 kHz in 46 steps
- Low distortion R-C oscillator
- Variable output control
- Compact, fully portable, light weight
- **Low battery indicator**

Specifi	cations model
	3001
Frequency Range	x1 range 20 Hz to 1.5 kHz (23 steps), x100 range 2 kHz
	to 150 kHz (23 steps)
Accuracy	20 Hz through 100 kHz (±3% or less), 120 kHz and
	150 kHz (±5% or less)
Output Control	OdB/-20dB attenuator switch and variable amplitude control
Output impedance	approx. 600Ω
SINEWAVE CHARACTE	RISTICS
Output Voltage	>1.2V rms at max. setting (no load)
Output Flatness	(Short term) 20 Hz to 150 kHz ±0.5dB ( reference frequency 1 kHz)
Distortion	200 Hz—15kHz 0.5% (THD) or less, 50 Hz—28 kHz 0.1% (THD)
	or less, 20 Hz—100kHz 0.3% (THD) or less
SQUARE WAVE CHARA	CTERISTICS
Output Voltage	> 5V p-p at maximum setting
Rise and Fall Time	Less than 0.5microseconds
Sag	Less than 5% at 20 Hz (DC coupled)
Over Shoot	<2% from maximum output, to 50mV p-p
Duty Ratio	50% +5%
SYNC OUTPUT CHARA	CTERISTICS
Output Voltage	>1.2V rms (no load)
Output Impedance	$1 k\Omega + 5\%$
Other specifications same	e as sinewave characteristics
GENERAL INFORMATION	DN
Operating Temperature	0°C to +50°C; specifications apply from 10°C to 30°C, <80% R.H.
Storage Temperature	-20°C to +60°C, without battery
Power Requirements	9V battery NEDA 1604A
Battery Life	35 hours typical with Alkaline
Battery Indicator	LED indicates low battery
Dimensions (HxWxD)	6 x 3.3 x 0.9" (150 x 82 x 21mm)
Weight	7 oz. (200 g) including battery
	1

#### Accessories

One Year Warranty

SUPPLIED: Two standard banana plug to insulated clip test leads, 9V battery, Instruction manual