

Products

Applications

Design Tools

About Chilisin

Contact Us

PRODUCTS

Chilisin provides inductor turnkey solutions for Power, EMI and RF and global technical team to support its customers. Chilisin has become one of the few inductor suppliers capable of providing a complete "one-stop shopping" experience.



 BBSJ_160808

Home > Products > EMI Suppression Filters > Bead > BBSJ_160808

Note: Please be sure to request approval specifications that provide further details of the products. Kindly note that the content of these specifications are subject to change or may be discontinued without prior notice. This product may not be designed/used in medical or high risk applications without Chilisin approval. Please contact our sales department before ordering.



Part Number : BBSJ00100505601Y00

Status	MP 
Size Code(JIS/EIA)	1005/0402
Impedance Ω (at 100MHz)	600
Tolerance($\pm\%$)	25
Test Frequency	100 MHz,200 mV
RDC(Ω)Max	0.6
Rated Current(mA)Max	300
Operating Temperature	-55°C~125°C(Including self - temperature rise)
L(mm)	1.00 $\pm$ 0.10
W(mm)	0.5 $\pm$ 0.10
T(mm)	0.50 $\pm$ 0.10

1.Rate Current : Applied the current to coils, the temperature rise shall not be more than 30°C

P/N	BBSJ00100505601Y00
Part Numbering	
Dimensions	
Packing	   
Recommended Pattern	
Electrical Characteristics Curve	

[Back](#)

About Chilisin

> Media Center

> Corporate Overview

Downloaded from [Arrow.com](#).

Investor Relations

> News

> Financial Information

Careers

> Join Chilisin

> Work life in Chilisin



Tel: +886-3-5992646

Fax: +886-3-5999176

> Corporate Milestones

> Corporate Shareholders Area

> Learning Career Development

Address: No.29, Lane 301,
Tehhsin Rd., Hosin, Hukou,
Hsinchu 303, Taiwan (R.O.C.)

> Core Technology

> Corporate Governance

> Welfare System

> Certificates & Awards

> Quality and Social Responsibility

✉ sales@chilisin.com

> Announcement

> Video

> Site Map