

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 17.6 mm, mounting type: DIN rail: 35 mm, Color: gray



Key Commercial Data

| Packing unit | 1 pc |
|--------------------------------------|-----------|
| Weight per Piece (excluding packing) | 233.330 g |
| Country of origin | China |

Technical data

General

| Mounting type | DIN rail: 35 mm |
|---------------------|-----------------|
| Color | gray |
| Number of positions | 1 |

Electrical data

| Operating voltage | 277 V AC |
|--|----------------------------|
| | 60 V DC |
| Rated current I _N | 4 A |
| Rated short-circuit switching capacity I _{cn} | 7.5 kA (240 V AC/ 60 V DC) |
| | 5 kA (277 V AC) |

Dimensions

| Height | 81.4 mm |
|--------|---------|
| Width | 17.6 mm |
| Depth | 65.7 mm |

Ambient conditions

01/23/2019 Page 1 / 6



Technical data

Ambient conditions

| Degree of protection | IP20 |
|---------------------------------|--------------|
| Ambient temperature (operation) | -35 °C 70 °C |

Connection data


| Conductor cross section solid min. | 1 mm² |
|---------------------------------------|-------------------|
| Conductor cross section solid max. | 35 mm² |
| Conductor cross section flexible min. | 1 mm ² |
| Conductor cross section flexible max. | 35 mm² |
| Conductor cross section AWG min. | 18 |
| Conductor cross section AWG max. | 2 |
| Connection method | Screw |
| Tightening torque max | 2 Nm |

Standards and Regulations

| Standards/specifications | UL 1077 |
|--------------------------|-------------|
| | IEC 60947-2 |


Drawings

Diagram



Dimensional drawing





Classifications

eCl@ss

| eCI@ss 5.1 | 27141100 |
|------------|----------|
| eCl@ss 6.0 | 27141100 |
| eCI@ss 7.0 | 27141116 |
| eCl@ss 8.0 | 27141116 |
| eCl@ss 9.0 | 27141116 |

01/23/2019 Page 2 / 6



Classifications

ETIM

| ETIM 5.0 | EC000899 |
|----------|----------|
| ETIM 6.0 | EC000899 |

Approvals

Approvals

Approvals

UL Recognized / cUL Recognized / cULus Recognized

Ex Approvals

Approval details

UL Recognized



http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm

FILE E 140459

cUL Recognized



http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm

FILE E 140459

cULus Recognized



Accessories

Accessories

Bridge

Wiring bridge - TMC 7 B1 80 57 C - 1022238



Bus bar for TMC 71... circuit breakers (single phase) 17.8 mm pitch, up to 57 positions. Rated for 80 A (end feed) 600 V AC/1000 V DC. UL508 Listed for connection of UL1077 rated circuit breakers.

01/23/2019 Page 3 / 6



Accessories

Wiring bridge - TMC 7 B1 80 37 CA - 1022237



Terminal adapter - TMC 7 B1 TERM - 1022233



Wiring bridge end cover - TMC 7 B1 END CAP - 1022231



Terminal adapter - TMC 7 B BUS CAP - 1022224



Thermomagnetic device circuit breaker - TMC 7/8 AUX - 2908219



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 9 mm, mounting type: Snaps on to side of circuit breaker, Color: gray



Accessories

Thermomagnetic device circuit breaker - TMC 7/8 ALARM - 2908220



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 9 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 12VDC SHNT - 2908221



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 24VDC SHNT - 2908222



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 48VDC SHNT - 2908224



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 125VDC SHNT - 2908225



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray



Accessories

Thermomagnetic device circuit breaker - TMC 7/8 120VAC SHNT - 2908226



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 240VAC SHNT - 2908227



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Thermomagnetic device circuit breaker - TMC 7/8 277VAC SHNT - 2908228



Thermomagnetic device circuit breaker, number of positions: 1, connection method: Screw, cross section: 1 mm²- 35 mm², AWG: 18 - 2, width: 18 mm, mounting type: Snaps on to side of circuit breaker, Color: gray

Phoenix Contact 2019 @ - all rights reserved http://www.phoenixcontact.com