

APC Smart-UPS XL Battery Pack Tower/Rack Convertible 48V, rackmount with kit, 5U

SUA48XLBP

Overview

Lead time Usually Ships within 2 Weeks

Main

Main Input Voltage	48 V DC	
Product or component type	External battery pack	
Number of rack unit	5U	
Number of cables	1	
Battery type	Lead-acid battery	
Provided equipment	User manual	
Range of product	Smart-UPS Battery Systems	

Batteries & Runtime

Number of battery filled slots	0
Number of battery free slots	0
Number of battery replacement quantity	2
Additional information	For use with "SUA" 2200/3000VA 5U rack/tower models. Can be used with 3U models with SUA039 extension cable.
Replacement battery	RBC55 □

Physical

Colour	Black	
Height	444 mm	
Width	221 mm	
Depth	495 mm	
Net weight	66.36 kg	
Mounting preference	No preference	
Mounting mode	Rack-mounted with kit	
USB compatible	No	

Output

UPS type Line interactive

Environmental

Ambient air temperature for operation	040 °C
Relative humidity	095 %
Operating altitude	010000 ft
Ambient air temperature for storage	-1545 °C
Storage Relative Humidity	095 %
Storage altitude	015240 m

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	52.000 cm
Package 1 Width	60.000 cm
Package 1 Length	77.000 cm
Package 1 Weight	81.000 kg

Contractual warranty

Warranty 2 years repair or replace



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint	
Total lifecycle Carbon footprint	348
Environmental Disclosure	Product Environmental Profile

Use Better

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
SCIP Number	080b8d64-796e-42e7-a17d-31b86e55d143
REACh Regulation	REACh Declaration

Use Again

○ Repack and remanufacture	
End of life manual availability	End of Life Information
Removable battery	User replaceable
Take-back	No

Image of product / Alternate images

Alternative



