

Online Catalog

Welcome to Laird Technologies' Online Catalog.



HOME > ONLINE CATALOG

Antennas & Reception Solutions

Vehicular Antennas & Telematics
Base Station & Backhaul Antennas
In-Building, CPE, Access Point, &
Mobile Client Antennas
RFID Antennas
Mobile Radio Antennas

EMI Solutions

EMI Shielding & Gaskets
Specialty EMI Solutions
Ferrite Products

Thermal Management Solutions

Thermal Interface Materials
Thermally Conductive PCB Materials
Thermoelectric Assemblies
Thermoelectric Modules
Liquid Cooling Systems

Wireless Solutions & M2M

Telematics & Tracking Devices
Proprietary Radio Modules
Bluetooth Radio Modules
Summit Wireless Wi-Fi® Radio
Modules

Search Catalog

SEARCH

[All Categories](#) > [EMI Solutions](#) > [Ferrite Products](#) > [Ferrite Cable Cores](#) > [Round and Cylindrical Cores](#) > [Low Frequency Ferrite Cores](#) > [Item # LFB143064-000](#)

Request Information

Item # LFB143064-000, Low Frequency Ferrite Cores

[Printable Page](#)


[Email This Page](#)

[Save To Favorites](#)

Stock Locator



[larger image](#)



[larger image](#)

MORE IMAGES

- [Turn](#)
- [Impedance Curves](#)

DOWNLOADS

- [Cable Core Catalog](#)
(, 0KB)
- [View Print](#)
(, 0KB)

Specifications

Dimension A	14.27 mm
Dimension B	6.35 mm
Dimension C	28.58 mm
Net Z at 500 KHz (1 Turn)	70
Net Z at 500 KHz (2 Turn)	290
Net Z at 500 KHz (3 Turn)	650
Net Z at 500 KHz (5 Turn)	1757
Net Z at 500 KHz (10 Turn)	7573
Net Z at 1 MHz (1 Turn)	122
Net Z at 1 MHz (2 Turn)	490
Net Z at 1 MHz (3 Turn)	1100
Net Z at 1 MHz (5 Turn)	2842
Net Z at 1 MHz (10 Turn)	11774
Net Z at 5 MHz (1 Turn)	120
Net Z at 5 MHz (2 Turn)	480
Net Z at 5 MHz (3 Turn)	1080
Net Z at 5 MHz (5 Turn)	2646
Net Z at 5 MHz (10 Turn)	7364
Material Type	Low Frequency Material
Product Type Code	Round Cylindrical Cores
Part Size Code	143064
Additional Description	Standard Part

Request Information