

#### Product Search Data Sheet

Please download the latest datasheet of CSTLS16M0X51Z-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTLS16M0X51Z-B0

Note: This datasheet may be out of date.

# CSTLS16M0X51Z-B0












### **Applications**

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Industrial	
	Equipment	
	Please refer to Our Website and	
	specifications, etc. for information about	
Specific	the performance, functions, quality,	
Applications	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



# Appearance & Shape







## Packaging Information

Packaging	Specifications	Standard Packing Quantity
В0	Bulk	500



#### **Features**

MURATA's ceramic resonator, CERALOCK has been widely applied as the most suitable component for clock oscillators in a broad range of microprocessors.

The CSTLS series can be used in the design of oscillation circuits not requiring external load capacitors, enabling both high-density mounting and cost reduction.

#### **Features**

- 1. Oscillation circuits do not require external load capacitors. There is some variation in capacitance values applicable to various IC.
- 2. Stable over a wide temperature range.
- 3. Compact, lightweight and exhibit superior shock resistance performance.
- 4. Enable the design of oscillator circuits requiring no adjustment.
- 5. Cost-effective and reliable availability.

1 of 2

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





### Product Search Data Sheet

#### Note: This datasheet may be out of date. Please download the latest datasheet of CSTLS16M0X51Z-B0 from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=CSTLS16M0X51Z-B0

# CSTLS16M0X51Z-B0



# **Specifications**

Product Type	Ceramic Resonator
,	(CERALOCK)
Series	CSTLS_X
Frequency	16.000MHz
Frequency Tolerance	+/-0.50% max.
Operating Temperature Range	-40°C~125°C
Frequency Shift by	
Temperature	+/-0.30% max.
Frequency Aging	+/-0.20% max.
Resonant Impedance (R1)	50ohm max.
Built-in Load Capacitance (CL1/CL2)	5pF
(CL 1/CLZ)	
Shape	Lead
Wash	Not available
L x W (size)	6.5x7.0mm
Mass	179mg

2 of 2

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

