

44 Series Insertion & Removal Tools

P/N's 356-258, 356-259, & 356-260

DATA SHEET

Amphenol offers three hand tools for the insertion and removal of their 44 Series contacts (P/N's 44-100-1414P & 44-102-1414S) from their connectors.

P/N 356-258 (Insertion Tool for Pin & Socket Contacts). Pull wire back through tool until the tip of the tool seats against the contact shoulder. Slowly push the contact straight into the cavity (through back of connector) until the insertion bit shoulder rests against the connector. Release wire and pull out the tool. Check retention by pulling gently on wire.

P/N 356-258



P/N 356-259 (Removal Tool for Pin Contacts). From front of connector (mating side) the contact removal tool slides over (encapsulates) the pin and you slowly push the contact out of the connector. Once the wire contact assembly is removed through the back of the connector remove the tool from the front.

P/N 356-259



P/N 356-260 (Removal Tool for Socket Contacts). From front of connector (mating side) the contact removal tool slides inside the socket portion of the contact and you slowly push the contact out of the connector. Once the wire contact assembly is removed through the back of the connector remove the tool from the front.

P/N 356-260



AMPHENOL CANADA CORPORATION
605 Milner Avenue
Toronto, Ontario
Canada, M1B 5X6
(416) 291-4401