

Online Catalog

Welcome to Laird Technologies' Online Catalog.



HOME > ONLINE CATALOG

Antennas & Reception Solutions

Vehicular Antennas & Telematics
Base Station & Backhaul Antennas
In-Building, CPE, Access Point, &
Mobile Client Antennas
RFID Antennas
Mobile Radio Antennas

EMI Solutions

EMI Shielding & Gaskets
Specialty EMI Solutions
Ferrite Products

Thermal Management Solutions

Thermal Interface Materials
Thermally Conductive PCB Materials
Thermoelectric Assemblies
Thermoelectric Modules
Liquid Cooling Systems

Wireless Solutions & M2M

Telematics & Tracking Devices
Proprietary Radio Modules
Bluetooth Radio Modules
Summit Wireless Wi-Fi® Radio
Modules

Search Catalog

Keyw ord

SEARCH

[All Categories](#) > [EMI Solutions](#) > [Ferrite Products](#) > [Ferrite Cable Cores](#) > [Round and Cylindrical Cores](#) > [Low Frequency Ferrite Cores](#) > [Item # LFB187102-000](#)

Request Information

Item # LFB187102-000, Low Frequency Ferrite Cores

[Printable Page](#)


[Email This Page](#)

[Save To Favorites](#)

Stock Locator



[larger image](#)



[larger image](#)

MORE IMAGES

- [Turn](#)
- [Impedance Curves](#)

DOWNLOADS

[Cable Core Catalog](#)
(, 0KB)

[View Print](#)
(, 0KB)

Specifications

Dimension A	18.67 mm
Dimension B	10.16 mm
Dimension C	28.58 mm
Net Z at 500 KHz (1 Turn)	53
Net Z at 500 KHz (2 Turn)	200
Net Z at 500 KHz (3 Turn)	430
Net Z at 500 KHz (5 Turn)	1182
Net Z at 500 KHz (10 Turn)	4766
Net Z at 1 MHz (1 Turn)	91
Net Z at 1 MHz (2 Turn)	350
Net Z at 1 MHz (3 Turn)	780
Net Z at 1 MHz (5 Turn)	1969
Net Z at 1 MHz (10 Turn)	8190
Net Z at 5 MHz (1 Turn)	84
Net Z at 5 MHz (2 Turn)	330
Net Z at 5 MHz (3 Turn)	770
Net Z at 5 MHz (5 Turn)	1863
Net Z at 5 MHz (10 Turn)	5930
Material Type	Low Frequency Material
Product Type Code	Round Cylindrical Cores
Part Size Code	187102
Additional Description	Standard Part

Request Information