

## DLW43MH201XK2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW43MH201XK2# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=DLW43MH201XK2%23

"#"at the end indicates the package specification code.

For 100Base-T1









### < List of part numbers with package codes >

DLW43MH201XK2B

DLW43MH201XK2K

DLW43MH201XK2L




### **Applications**

Unsuitable	Please be sure to read and comply with
Applications	these "Precautions for use."
Specific Applications	Automotive powertrain/safety equipment, Automotive infotainment/comfort equipment,Medical equipment [GHTF A/B/C] except for implant & surgery & auto injector Please refer to Our Website and specifications, etc. for information about the performance, functions, quality, management, and safety required for the above applications, and use Products after confirming the performance and reliability of the actual Product.
Recommended	Automotive powertrain/safety equipment,
Applications	Automotive Ethernet



## Appearance & Shape







### Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
К	330mm Embossed Tape	2500
L	180mm Embossed Tape	500



### **Features**

- 1. Small size: L4.5xW3.2xT2.7mm (EIAcode: 1812) Tolerance: 0.2mm
- 2. It realized common mode inductance of 200microH (at 0.1MHz) though it is small size.
- 3. Transfer mode conversion characteristics is properly improved.

### **Applications**

Noise countermeasures for the automotive market, in particular for the vehicle LAN BroadR-Reach™

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





## DLW43MH201XK2#

Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW43MH201XK2# from the official website of Murata

http://www.murata.com/en-gb/products/productdetail?partno=DLW43MH201XK2%2

"#"at the end indicates the package specification code.



# Specifications

Shape	SMD
Size Code (in mm)	4532
Size Code (in inch)	1812
Length	4.5mm
Length Tolerance	±0.2mm
Width	3.2mm
Width Tolerance	±0.2mm
Thickness	2.7mm
Thickness Tolerance	±0.2mm
Rated Current	110mA
Derating of Rated Current	No
Rated Voltage	20Vdc
Withstanding Voltage	50Vdc
DC Resistance(max.)	4.5Ω
DC Resistance	4.5Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 105°C
Mass(typ.)	0.16g
Number of Circuit	1
Common Mode Inductance	200µH-25%/+50% (at 0.1MHz)
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

2 of 3

#### Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# DLW43MH201XK2#


Note: If you have not downloaded this document from our official website, please note that the information provided may not be the most current.

Please download the latest datasheet of DLW43MH201XK2# from the official website of Murata


http://www.murata.com/en-qb/products/productdetail?partno=DLW43MH201XK2%23

"#"at the end indicates the package specification code.





Impedance-Frequency Characteristics



**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

