





WAGO-I/O-CHECK is an easy-to-use Windows application for operating and displaying a WAGO I/O System 750's node without connecting to a fieldbus system.

The software reads the configuration from the node and displays it graphically on the screen. This graphic can be printed together with a configuration list as documentation.

With WAGO-I/O-CHECK, it is possible to display and specify the process data of the I/O modules. The field wiring, including all sensors and actuators, can thus be checked before startup.

For some types of interface, Pt100 and thermocouple modules, application-specific settings can be made, such as the baud rate or sensor types. The coupler must be connected to a free serial or USB port of the PC using the communication cable supplied in the set with the system to enable communication between WAGO-I/O-CHECK and the node.

System requirements	
Supported operating systems	Windows 7 Windows 10
Processor	1 GHz or higher, with 32 bits (x86) or 64 bits (x64)
Memory	Min. 1 GB RAM 2 GB RAM or more (recommended)
Hard disk space	min. 150 MB
Graphics resolution	1024 x 786 (min.), 1280 x 1024 or higher (recommended)

Delivery	
Delivery type	Installation file (CD-ROM)
Scope of delivery	CD-ROM with software and serial communication cable (750-920)

Commercial data	
PU (SPU)	1 pcs
Packaging type	Box
Country of origin	DE
GTIN	4045454394899
Customs tariff number	85234920009

Data Sheet | Item Number: 759-302

https://www.wago.com/759-302



Product classification

UNSPSC 43232605

Environmental Product Compliance

RoHS Compliance Status Compliant, No Exemption

Downloads

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 759-302



Documentation

O-SYSTEM 750

Manual

Product Manual WAGO- V 1.2.0 pdf
I/O-CHECK Commissioning Tool for WAGO-I/

 System Description
 pdf

 Software − General
 pdf

 Product Information
 368.80 KB

Bid Text			
759-302	19.02.2019	xml 4.80 KB	\perp
759-302	10.01.2019	docx 16.26 KB	$\underline{\downarrow}$

Subject to changes. Please also observe the further product documentation!

Current addresses can be found at:: $\underline{www.wago.com}$