

Data Sheet | Item Number: 745-682

Jumper; 2-way; unplated; silver-colored

<https://www.wago.com/745-682>



Color: ■ silver-colored

Similar to illustration

Electrical data

Ratings per IEC/EN

| | |
|---------------|------|
| Rated current | 76 A |
|---------------|------|

Physical data

| | |
|-------------------|----------------------|
| Pin spacing | 20 mm / 0.787 inches |
| Jumper assignment | 1-2 |

Mechanical data

| | |
|----------|--|
| Suitable | for 745 Series (16 mm ²) and 2716 Series |
|----------|--|

Material data

| | |
|----------------------|--|
| Note (material data) | Information on material specifications can be found here |
| Color | silver-colored |
| Contact material | Copper alloy |
| Contact Plating | Tin |
| Fire load | 0 MJ |
| Weight | 4.3 g |

Commercial data

| | |
|-----------------------|--------------------------------|
| Product Group | 4 (Printed Circuit Connectors) |
| PU (SPU) | 400 (50) pcs |
| Packaging type | Box |
| Country of origin | CH |
| GTIN | 4044918303538 |
| Customs tariff number | 85366990990 |

Product Classification

| | |
|-------------|----------------------|
| UNSPSC | 39121421 |
| eCl@ss 10.0 | 27-14-11-40 |
| eCl@ss 9.0 | 27-44-04-92 |
| ETIM 9.0 | EC000489 |
| ETIM 10.0 | EC000489 |
| ECCN | NO US CLASSIFICATION |

Environmental Product Compliance

| | |
|------------------------|-------------------------|
| RoHS Compliance Status | Compliant, No Exemption |
|------------------------|-------------------------|

Downloads

Environmental Product Compliance

| | | | |
|--|--|--|--|
| Compliance Search | | | |
| Environmental Product Compliance 745-682 | | | |


Documentation

| | | | |
|-------------------------------|------------|-------------------|--|
| Additional Information | | | |
| Technical Section | 03.04.2019 | pdf 2027.26 KB | |


CAD/CAE-Data

| | | | |
|----------------------|--|--|--|
| CAD data | | | |
| 2D/3D Models 745-682 | | | |


Installation Notes



Inserting a comb-style jumper bar.



To insert a comb-style jumper bar, push it down using a screwdriver until it hits the backstop – 745 Series.



To remove the jumper bar, lift it up using a screwdriver – 745 Series.