## HUBER+SUHNER® DATA SHEET Coaxial PCB Connector: 85 1023-C50-0-1/111 N



## Description

Right angle PCB jack

Interface Standards DIN 41626/2



## **Technical Data**

**Electrical Data** 

 $\begin{array}{ll} \text{Impedance} & \quad \text{50 } \Omega \\ \text{Interface frequency max.} & \quad \text{4 GHz} \end{array}$ 

**Mechanical Data** 

Board mounting type through holes Weight 0.0025 kg

**Environmental Data** 

Operating Temperature -55 °C to 125 °C 2002/95/EC (RoHS) compliant

**Material Data** 

Piece Parts Material

Centre contact Copper Beryllium Alloy
Outer contact Brass
Body Brass
Insulator PFA / PTFE

**Related Documents** 

Outline drawing DOU-00013127 Catalogue drawing DCA-00013129

**Ordering Information** 

Single package 85 1023-C50-0-1/111 NE

Remarks

PCB connector with stand-offs

**Surface Plating** 

Hard Au min. 1.3 μm over Ni min. 1.3 μm Gold Plating (Nickel underplated) Hard Au min. 0.8 μm over Ni min. 1.3 μm

HUBER+SUHNER is certified according to ISO 9001 and ISO 14001

WAIVER!

It is exclusively in written agreements that we provide our customers with warrants and representations as to the technical contained specifications and/or the fitness for any particular purpose. The facts and figures herein are carefully compiled to the best of our knowledge, but they are intended for general informational purposes only.

**HUBER+SUHNER – Excellence in Connectivity Solutions** 

Document: DOC-0000193419 G Issued: 11.03.11



HUBER+SUHNER AG
RF Technology
9100 Herisau, Switzerland
Phone +41 (0)71 353 41 11
Fax +41 (0)71 353 45 90

www.hubersuhner.com

Uncontrolled Copy

Page 1/1