TE Internal #: CONBNC001

BNC Connector, Jack, 50 ohm, Bayonet, 3 GHz, Cable-to-Board, 1

Position, Printed Circuit Board, Board Mount, Brass, Nickel, 1

Coaxial Contacts

View on TE.com >



#### Connectors > RF Connectors > Coax Connectors



RF Interface: BNC

RF Connector Style: **Jack** 

Impedance:  $50 \Omega$ 

RF Connector Coupling Mechanism: Bayonet

RF Connector Coupling Mechanism

Connector Mounting Type

Operating Frequency: 3 GHz

### **Features**

### **Product Type Features**

Froduct Type realures	
Connector Product Type	Connector Assembly
RF Interface	BNC
RF Connector Style	Jack
Connector System	Cable-to-Board
Sealable	No
Connector & Contact Terminates To	Printed Circuit Board
Configuration Features	
Number of Positions	1
Number of Coaxial Contacts	1
Electrical Characteristics	
Impedance	50 Ω
Body Features	
Body Material	Brass
Body Plating Material	Nickel
Mechanical Attachment	

Bayonet

**Board Mount** 



### Operation/Application

Circuit Application	Signal
Operating Frequency	3 GHz
Other	

Polytetrafluoroethylene (PTFE)

## **Product Compliance**

Dielectric Material

For compliance documentation, visit the product page on TE.com>

EU RoHS Directive 2011/65/EU	Compliant
EU ELV Directive 2000/53/EC	Not Yet Reviewed
China RoHS 2 Directive MIIT Order No 32, 2016	No Restricted Materials Above Threshold
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JAN 2025 (247) Candidate List Declared Against: JUNE 2024 (241) Does not contain REACH SVHC
Halogen Content	Low Halogen - Br, Cl, F, I < 900 ppm per homogenous material. Also BFR/CFR/PVC Free
Solder Process Capability	Not reviewed for solder process capability

#### Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulations, TE's information on SVHC in articles for this part number is still based on the European Chemical Agency (ECHA) 'Guidance on requirements for substances in articles' (Version: 2, April 2011), applying the 0.1% weight on weight concentration threshold at the finished product level. TE is aware of the European Court of Justice ruling of September 10th, 2015 also known as O5A (Once An Article Always An Article) stating that, in case of 'complex object', the threshold for a SVHC must be applied to both the product as a whole and simultaneously to each of the articles forming part of its composition. TE has evaluated this ruling based on the new ECHA "Guidance on requirements for substances in articles" (June 2017, version 4.0) and will be updating its statements accordingly.

# Compatible Parts





TE Part # 1-1337420-0 BNC Str Plg MC 500hm Nickel Pltd RG58C/U



TE Part # 2484792-1 BNC Plug Str RG174 188A 316 4 GHz 50 Ohm



TE Part # 1-5227079-6 COMM BNC PLUG



TE Part # 1-1337429-0 BNC Str Plg Hex 75Ohm Silver Pltd RG59B/



# Customers Also Bought




TE Part #CONBNC002 BNC Jack 50 Ohm PCB Through Hole




TE Part #CONREVSMA007















TE Part #4-2840621-1 2POS,HC-STAK 25,HDR ASSY,COD A, FDU, PH 3

## **Documents**

BNC Connector, Jack, 50 ohm, Bayonet, 3 GHz, Cable-to-Board, 1 Position, Printed Circuit Board, Board Mount, Brass, Nickel, 1 Coaxial Contacts



### **Product Drawings**

BNC Jack 50 Ohm PCB Through Hole

English

### **CAD Files**

**Customer View Model** 

ENG\_CVM\_CVM\_CONBNC001\_A.2d\_dxf.zip

English

**Customer View Model** 

ENG\_CVM\_CVM\_CONBNC001\_A.3d\_igs.zip

English

3D PDF

3D

**Customer View Model** 

ENG\_CVM\_CVM\_CONBNC001\_A.3d\_stp.zip

English

By downloading the CAD file I accept and agree to the **Terms and Conditions** of use.

## Datasheets & Catalog Pages

**BNC Jack PCB Through-Hole Connector** 

English