

www.ti.com

# **Dual-Channel High-Speed ESD Protection Device**

Check for Samples: TPD2E2U06

## **FEATURES**

- **Provides System-Level ESD Protection for** Low-Voltage IO Interface
- IEC 61000-4-2 Level 4
  - ±25 kV (contact discharge)
  - ±30 kV (air-gap discharge)
- IO Capacitance 1.5 pF (Typ) •
- DC Breakdown Voltage 6.5 V (Min) .
- Ultra-Low Leakage Current 10 nA (Max)
- Low ESD Clamping Voltage
- Industrial Temperature Range: -40°C to +125°C
- Small Easy-to-Route DRL Package


## **APPLICATIONS**

- **Gaming Machines**
- eBook
- **Portable Media Players**
- **Digital Camera**

## DESCRIPTION

The TPD2E2U06 is a dual-channel ultra-low capacitance ESD-protection device. The device offers ±25-KV IEC contact and ±30-KV IEC air-gap ESD protection. The 1.5-pF line capacitance of the TPD2E2U06 makes the device suitable for a wide range of applications. Typical application interfaces are USB 2.0, LVDS, and I<sup>2</sup>C<sup>™</sup>.







Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet. I<sup>2</sup>C is a trademark of NXP Semiconductors.

# TPD2E2U06



#### SLLSEG9A-JUNE 2013-REVISED JUNE 2013



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

## **ABSOLUTE MAXIMUM RATINGS**

over operating free-air temperature range (unless otherwise noted)

		MIN	MAX	UNIT
$I_{PP}$	Peak pulse current (tp = 8/20 μs)		5.5 <sup>(1)</sup>	А
$P_PP$	Peak pulse power (tp = 8/20 µs)		85 <sup>(1)</sup>	W
	IEC 61000-4-2 air-gap ESD		±30 <sup>(1)</sup>	kV
	IEC 61000-4-2 contact ESD		±25 <sup>(1)</sup>	kV
	Operating temperature	-40	125	°C
	Storage temperature	-65	155	°C

(1) Measured at 25°C.

# **ELECTRICAL CHARACTERISTICS**

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
V <sub>RWM</sub>	Reverse stand-off voltage	I <sub>IO</sub> < 10 μA			5.5	V
V <sub>CLAMP</sub>	IO to GND	$I_{PP} = 1 \text{ A}, \text{ TLP}^{(1)}$		9.7		
		$I_{PP} = 5 \text{ A}, \text{ TLP}^{(1)}$		12.4		V
V <sub>CLAMP</sub>	GND to IO	$I_{PP} = 1 \text{ A}, \text{ TLP}^{(1)}$		1.9		V
		$I_{PP} = 5 \text{ A}, \text{ TLP}^{(1)}$		4		V
R <sub>DYN</sub>	Dynamic resistance	IO to GND <sup>(2)</sup>		0.5		Ω
R <sub>DYN</sub>	Dynamic resistance	GND to IO <sup>(2)</sup>		0.25		Ω
CL	Line capacitance	$f = 1 \text{ MHz}, V_{\text{BIAS}} = 2.5 \text{ V}^{(3)}$		1.5	1.9	pF
C <sub>CROSS</sub>	Channel-to-channel input capacitance	Pin 4 = 0 V, f = 1 MHz, $V_{BIAS}$ = 2.5 V, between channel pins <sup>(3)</sup>		0.02	0.03	pF
$\Delta_{\text{CIO-TO-GND}}$	Variation of channel input capacitance	Pin 4 = 0 V, f = 1 MHz, $V_{BIAS}$ = 2.5 V, channel_x pin to GND – channel_y pin to GND <sup>(3)</sup>		0.03	0.1	pF
V <sub>BR</sub>	Break-down voltage	I <sub>IO</sub> = 1 mA	6.5		8.5	V
I <sub>LEAK</sub>	Leakage current	V <sub>IO</sub> = 2.5 V		1	10	nA

Transmission Line Pulse with 10-ns rise time, 100-ns width. (1)

Extraction of RDYN Using least squares fit of TLP characteristics between I = 20 A and I = 30 A. (2)

Measured at 25°C. (3)

www.ti.com

SLLSEG9A-JUNE 2013-REVISED JUNE 2013

# DEVICE INFORMATION FUNCTIONAL BLOCK DIAGRAM

## Figure 1. CIRCUIT SCHEMATIC DIAGRAM

GND

#### **PIN FUNCTIONS**


	PIN	1/0	DESCRIPTION
NAME	NO.	I/O	DESCRIPTION
IO1	3	I/O	The IO1 and IO2 pins are an ESD protected channel. Connect these pins to the data line as
IO2	5	I/O	close to the connector as possible.
NC	1, 2	-	This pin is not connected and is left floating, grounded, or connected to VCC.
GND	4	-	The GND (ground) pin is connected to ground.

# **TPD2E2U06**

TEXAS INSTRUMENTS


#### SLLSEG9A-JUNE 2013-REVISED JUNE 2013

www.ti.com





SLLSEG9A-JUNE 2013-REVISED JUNE 2013





26-Aug-2013

# PACKAGING INFORMATION

Orderable Device	Status	Package Type	Package	Pins	Package	Eco Plan	Lead/Ball Finish	MSL Peak Temp	Op Temp (°C)	Device Marking	Samples
	(1)		Drawing		Qty	(2)		(3)		(4/5)	
TPD2E2U06DRLR-P	ACTIVE	SOT	DRL	5	4000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM		DT6	Samples

<sup>(1)</sup> The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

<sup>(2)</sup> Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes. **Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

<sup>(3)</sup> MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

<sup>(4)</sup> There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

**Important Information and Disclaimer:**The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.


# PACKAGE MATERIALS INFORMATION

www.ti.com

Texas Instruments

### TAPE AND REEL INFORMATION





## QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal
-----------------------------


Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPD2E2U06DRLR-P	SOT	DRL	5	4000	180.0	8.4	1.98	1.78	0.69	4.0	8.0	Q3

TEXAS INSTRUMENTS

www.ti.com

# PACKAGE MATERIALS INFORMATION

24-Aug-2013




\*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPD2E2U06DRLR-P	SOT	DRL	5	4000	202.0	201.0	28.0

DRL (R-PDSO-N5)

# PLASTIC SMALL OUTLINE



NOTES:

A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
B. This drawing is subject to change without notice.

 Body dimensions do not include mold flash, interlead flash, protrusions, or gate burrs. Mold flash, interlead flash, protrusions, or gate burrs shall not exceed 0,15 per end or side.
D. JEDEC package registration is pending.



#### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have *not* been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products		Applications	
Audio	www.ti.com/audio	Automotive and Transportation	www.ti.com/automotive
Amplifiers	amplifier.ti.com	Communications and Telecom	www.ti.com/communications
Data Converters	dataconverter.ti.com	Computers and Peripherals	www.ti.com/computers
DLP® Products	www.dlp.com	Consumer Electronics	www.ti.com/consumer-apps
DSP	dsp.ti.com	Energy and Lighting	www.ti.com/energy
Clocks and Timers	www.ti.com/clocks	Industrial	www.ti.com/industrial
Interface	interface.ti.com	Medical	www.ti.com/medical
Logic	logic.ti.com	Security	www.ti.com/security
Power Mgmt	power.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video
RFID	www.ti-rfid.com		
OMAP Applications Processors	www.ti.com/omap	TI E2E Community	e2e.ti.com
Wireless Connectivity	www.ti.com/wirelessconne	ectivity	

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2013, Texas Instruments Incorporated