

Please download the latest datasheet of DLW43SH101XP2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH101XP2%23

Note: This datasheet may be out of date.

"#" indicates a package specification code.

Discontinued







< List of part numbers with package codes >

DLW43SH101XP2B

DLW43SH101XP2K

DLW43SH101XP2L




Applications

11 2 11	[B]	
Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Automotive powertrain/safety equipment,	
	Automotive infotainment/comfort	
	equipment,Consumer equipment,	
	Medical equipment [GHTF A/B/C]	
	except for implant & surgery & auto	
	injector,Industrial equipment except for	
	transportation & facility & energy	
Specific	equipment	
Applications	Please refer to Our Website and	
	specifications, etc. for information about	
	the performance, functions, quality,	
	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	
Recommended	Automotive powertrain/safety equipment,	
Applications	CAN [Controller Area Network],FlexRay	



Appearance & Shape







Packaging Information

		Standard
Packaging	Specifications	Packing
		Quantity
В	Bulk(Bag)	100
K	330mm Embossed Tape	2500
L	180mm Embossed Tape	500

1 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XP2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH101XP2%23

"#" indicates a package specification code.



Features

- 1. Small size: L4.5xW3.2xT2.7mm (EIAcode: 1812) Tolerance: +/-0.2mm
- 2. It realized common mode inductance of 100microH (at 0.1MHz) though it is small size.
- 3. Suitable for noise suppression from low frequency range (0.1MHz).

Applications

For Automotive.

Common mode noise suppression of automotive LAN for Flex Ray etc.

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date.

Please download the latest datasheet of DLW43SH101XP2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH101XP2%23

"#" indicates a package specification code.



Specifications

Chana	SMD
Shape	SMD
Size Code (in mm)	4532
Size Code (in inch)	1812
Length	4.5mm
Length Tolerance	±0.2mm
Width	3.2mm
Width Tolerance	±0.2mm
Thickness	2.7mm
Thickness Tolerance	±0.2mm
Rated Current	170mA
Derating of Rated Current	No
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	2Ω
DC Resistance	2.0Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 125°C
Mass(typ.)	0.17g
Number of Circuit	1
Common Mode Inductance	100µH-30%/+80% (at 0.1MHz)
Operating Temperature Range(Self-temperature rise is included)	No
Brand	Murata

3 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.




Note: This datasheet may be out of date.


Please download the latest datasheet of DLW43SH101XP2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=DLW43SH101XP2%23

"#" indicates a package specification code.







Impedance-Frequency Characteristics

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

