

# **Power Transformer Chassis Mount: Quick Pack**

# **FD7-120**

## **Description:**

The FD7-120 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

# Electrical Specifications (@25C):

Maximum Power: 56.0VA

Input Voltage:

**Series:** 230VAC@50/60Hz Parallel: 115VAC@50/60Hz Output Voltage: 120.0VCT@0.5A

**Hipot:** 2500VAC primary to secondary; 1500VAC windings to core.

#### Construction:

Split bobbin non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.



### **Dimensions:**


Α	В	С	D	Е	F	G
2.250	3.125	3.687	1.812	2.687	.187 Dia	1.062

Notes: 1. Units: inches.

2. Terminal size: .187" X 0.021".

3. Weight: 1.70 lbs

# **Schematic:**



**Input (115V):** Input 1 & 2

Connect 1&4, 2&5

Input (230V): Input 1 & 5

Connect 2&4

Output: 6 & 10

RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

Web: www.TriadMagnetics.com Phone 951-277-0757

Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571

Publish Date: May 29, 2019

