



Color: ■ green

| Mechanical data |                 |
|-----------------|-----------------|
| Suitable        | for 2070 Series |

| Material data |       |
|---------------|-------|
| Color         | green |
| Fire load     | 0 MJ  |
| Weight        | 1.8 g |

| Commercial data       |               |
|-----------------------|---------------|
| PU (SPU)              | 1 pcs         |
| Packaging type        | Box           |
| Country of origin     | DE            |
| GTIN                  | 4055143822930 |
| Customs tariff number | 39269097900   |


| Product Classification |                      |
|------------------------|----------------------|
| UNSPSC                 | 27111701             |
| eCl@ss 10.0            | 27-14-11-92          |
| eCl@ss 9.0             | 27-14-11-92          |
| ETIM 9.0               | EC002848             |
| ETIM 8.0               | EC002848             |
| ECCN                   | NO US CLASSIFICATION |

| Environmental Product Compliance |                        |
|----------------------------------|------------------------|
| RoHS Compliance Status           | Compliant,No Exemption |




| Downloads                                 |  |
|---|--|
| Environmental Product Compliance          |  |
| Compliance Search                         |  |
| Environmental Product Compliance 2070-400 |  |

## Installation Notes



Insert fine-stranded conductors and remove all conductor types via operating tool. Solid conductors can also be terminated by simply pushing them in.



Use an operating tool or simply "twist and pull" to remove solid conductors.